arXiv:chao-dyn/9803006v1 4 Mar 1998

Systematic Derivation of Amplitude Equations and Normal Forms for Dynamical Systems

M. Ipsen[†] F. Hynne[‡] P. G. Sørensen[‡]

February 5, 2008

Abstract

We present a systematic approach to deriving normal forms and related amplitude equations for flows and discrete dynamics on the center manifold of a dynamical system at local bifurcations and unfoldings of these. We derive a general, explicit recurrence relation that completely determines the amplitude equation and the associated transformation from amplitudes to physical space. At any order, the relation provides explicit expressions for all the nonvanishing coefficients of the amplitude equation together with straightforward linear equations for the coefficients of the transformation. The recurrence relation therefore provides all the machinery needed to solve a given physical problem in physical terms through an amplitude equation. The new result applies to any local bifurcation of a flow or map for which all the critical eigenvalues are semisimple (*i.e.* have Riesz index unity). The method is an efficient and rigorous alternative to more intuitive approaches in terms of multiple time scales. We illustrate the use of the method by deriving amplitude equations and associated transformations for the most common simple bifurcations in flows and iterated maps. The results are expressed in tables in a form that can be immediately applied to specific problems.

[†] UNI•C, Danish Computing Center for Research and Education. DTU, Building 304, DK-2800 Lyngby, Denmark.

[‡] Department of Chemistry, University of Copenhagen, H.C.Ørsted Institute, Universitetsparken 5, DK-2100 Copenhagen, Denmark.

The behavior of physical, chemical, and biological systems near the onset of dynamic instabilities has considerable importance. Here the dynamics can be described efficiently in a low-dimensional space of "amplitudes" by using so-called amplitude equations or normal forms. Amplitude equations like the complex Ginzburg-Landau equation have been widely used to describe the qualitative behavior of such systems. The paper provides a general method for setting up all the necessary equations to solve a given physical problem quantitatively in terms of amplitude equations.

For example, chemical oscillations and waves can be described by differential equations which near the onset of oscillation can be approximated in terms of complex amplitudes. This reduces the state space from the (possibly high-dimensional) concentration space to a complex plane. Such reductions usually result in immense savings in computational effort. To describe the dynamics in terms of amplitudes one must first of all determine the coefficients of the amplitude equation. For a quantitative study and comparison with experiments, one must also determine the transformation from amplitudes to the actual concentrations of all the chemical species. The paper provides tables of formulas for calculating all relevant coefficients. For instabilities not covered by the tables, the formulas can be calculated by a simple recurrence relation, the main result of the paper.

1 Introduction

The present work grew out of a need to extend the complex Ginzburg-Landau equation for a chemical reaction-diffusion problem [1, 2]. In the process it became clear that a systematic and efficient method of deriving amplitude equations and associated transformations for local bifurcations is lacking. We provide such a method for an important class of bifurcations in the present paper.

Briefly, the idea of an amplitude equation for an oscillatory system is to represent the state of the system through a complex amplitude (real amplitude and phase) which varies much more slowly in space and time than the original dynamical variables. A slow variation of an amplitude as compared with much faster oscillations apply near a supercritical Hopf bifurcation. In fact, the concept of an amplitude can be generalized to non-oscillatory modes near local bifurcations.

A large difference of characteristic times of variation of amplitudes versus period of oscillation, is the basis of traditional "methods of multiple times" [3–6] to derive amplitude equations. Unfortunately, such methods are somewhat intuitive (as opposed to rigorous) and are not easy to generalize. The property utilized in amplitude equations is the critical slowing down of modes associated with a bifurcation. This means that amplitude equations can be related to normal forms describing the essential features of the motion of a state point in the center manifold at a bifurcation. In this paper, we suggest a precise and general definition of amplitude equations associated with local bifurcations of a flow or iterated map and develop a systematic method of deriving them. We emphasize that the present work does not require any use of normal form theory. In fact, the derivation of the traditional normal form theorem appears naturally as part of the theory developed in this paper.

We restrict the discussion to bifurcations associated with spatially homogeneous systems and exclude *e.g.* Turing bifurcations. Consequently, we shall treat systems defined by ordinary differential equations or iterated maps. The theory can be generalized to spatially inhomogeneous systems *e.g.* with a linear diffusion operator.

The idea of the method proposed is the following. Consider a dynamical system at a local bifurcation. The motion of the state point in the r-dimensional center manifold W^{c} is described by r (generalized) amplitudes z_j ($j = 1, \ldots, r$). These are coordinates of a point $\mathbf{z}$ in the center subspace E^{c} with respect to a basis of eigenvectors of the linearized vector field or map $\mathbf{J}$. We assume that $\mathbf{J}$ has r linearly independent eigenvectors in E^{c}, but make no assumptions about the other modes.

For a flow, we derive a set of differential equations for the amplitudes z_j, the amplitude equation, and a transformation $\mathbf{h}(\mathbf{z})$ from E^{c} to W^{c} so that the image $\mathbf{h}\big(\mathbf{z}(t)\big)$ describes the dynamical evolution of the state point on W^{c} when $\mathbf{z}(t)$ is the appropriate solution to the amplitude equation.

The transformation $\mathbf{h}(\mathbf{z})$ is determined by the condition that as many coefficients of the amplitude equation as possible must vanish, *i.e.* it is a special type of normal form transformation. The non-vanishing coefficients of the amplitude equation are determined together with the transformation $\mathbf{h}(\mathbf{z})$, order by order in an iterative process. The method is very efficient — in one process, it determines the amplitude equation (in normal form) and its unfolding as well as the center manifold. Initially, all that is required is to determine the non-hyperbolic eigenvalues of the Jacobian $\mathbf{J}$ and the corresponding right and left eigenvectors. (Thus, it is not necessary to transform $\mathbf{J}$ into Jordan block form.) At each order of iteration, the only non-trivial calculations are the solution of a few systems of linear equations. The center manifold is then locally determined by the transformation $\mathbf{h}(\mathbf{z})$ that immediately provides the physical solution from that of the amplitude equation. Other representations of the geometry of the center manifold can easily be obtained from $\mathbf{h}(\mathbf{z})$. The method for iterated maps (including Poincaré maps associated with periodic solutions to flows) is similar to that just described for flows.

The method reported here makes it straightforward to solve a given physical (chemical, biological, ...) problem in terms of an amplitude description. Once the general explicit formulas have been derived for the type of bifurcation in question, the coefficients of the amplitude equation and the transformation $\mathbf{h}(\mathbf{z})$ can be calculated for the particular problem directly in terms of the vector field (or map). So the amplitude equation for the particular physical problem can be written down immediately, and any solution to it in terms of amplitudes can then be expressed in terms of real physical quantities through the transformation $\mathbf{h}(\mathbf{z})$. To illustrate the method, we derive general formulas for the most common simple bifurcations for flows as well as iterated maps. A more challenging application of the method to derive an amplitude equation for an extension of the complex Ginzburg-Landau equation in the context of fold-Hopf bifurcations in reaction-diffusion problems will be published separately.

A method similar to the one developed here has been obtained previously by Bruno [7] (and see the references therein) for the general case. However, the restriction to semisimple critical eigenvalues allows us to derive results for any such bifurcation in particularly simple form. These results, a recurrence relation (28) with (29) for flows and (54) for iterated maps, provide explicit expressions for the amplitude equation (or normal form), (31) and (55) respectively, and explicit linear equations for the transformation from amplitudes to physical space, (30) and (56) respectively. It is entirely straightforward to obtain all the nonvanishing coefficients of the amplitude equation and the associated transformation, order by order to any desired order, and to apply these to specific physical problems.

Explicit results for a number of specific bifurcations, applicable at the bifurcation points, can also be found in the recent book by Kutznetsov [8]. Other approaches are described for example by Guckenheimer & Holmes [9], Coullet & Spiegel [10], Elphick *et al.* [11], and by Golubitsky *et al.* [12]. For a more physically oriented discussion, see also Crawford [13]. Other important techniques for obtaining information on the dynamics in a vicinity of bifurcation points are perturbation methods which have been reviewed in detail by Iooss & Joseph [14] and Hassard *et al.* [15]. These approaches generally provide series expansions of the non-trivial steady or periodic solutions that emerge at the bifurcation points.

The paper is organized as follows. In Section 2, we develop the amplitude description for flows on the center manifold. Section 3 extends the results to describe the unfolding of the derived amplitude equation. The corresponding theory for iterated maps is very similar to that for flows and is given in Section 4. Section 5 illustrates the use of the general method by deriving amplitude equations and transformation equations for the most common simple bifurcations. It presents the results as convenient tables that can be used immediately for any specific physical problem covered by the tables. We illustrate the use of the tables in appendix A by deriving amplitude equations and transformations for some well-known systems.

Amplitudes as initially defined in this paper (Sections 2 and 4) have simple geometric significance, common to all bifurcations for flows and iterated maps. However, for oscillatory modes, it is advantageous to introduce the concept of "proper amplitudes", which are complex variables for which both modulus and argument vary slowly. These proper amplitudes agree with accepted usage. It is then possible to scale time and amplitudes for all bifurcations so that the scaled amplitude equations become independent of the distance from the bifurcation point to lowest order — we define proper amplitudes to incorporate such scaling. Scalings and proper amplitudes are discussed in Section 6.

The physical interpretation of unfoldings of amplitude equations is discussed in Section 7 aiming at a more intuitive understanding of their meaning. Section 8 discusses some features of the solutions to amplitude equations, transformed back to the original physical space, *i.e.* solutions in physical terms to physical problems. Such back transformation is an important part of the solution and it follows naturally from the present method. In the final Section 9, we summarize and discuss the results of this paper.

2 Amplitude equations for flows

We start by considering a flow on $\mathbb{R}^n$

$$\dot{\mathbf{x}} = \mathbf{F}(\mathbf{x}) = \mathbf{J}\cdot\mathbf{x} + \mathbf{f}(\mathbf{x}), \tag{1}$$

with a stationary solution $\mathbf{x} = \mathbf{0}$. Here, the vector field on the right-hand side has been split into linear and nonlinear parts $\mathbf{J}\cdot\mathbf{x}$ and $\mathbf{f}(\mathbf{x})$. We assume that $\mathbf{J}$ has r distinct right eigenvectors $\mathbf{u}_j$ and left eigenvectors $\mathbf{u}_j^*$ corresponding to r critical eigenvalues λ_j with zero real part ($j = 1, \ldots, r$), chosen to satisfy the biorthonormality conditions

$$\mathbf{u}_i^*\cdot\mathbf{u}_j = \delta_{ij}, \quad \text{for} \quad i, j = 1, \ldots, r, \tag{2}$$

where δ_{ij} is the usual Kronecker delta. The r eigenvectors span the r-dimensional center subspace E^{c}. As discussed in [9], the center manifold W^{c} can be locally parameterized by points $\mathbf{z} \in E^{\mathrm{c}}$ through a smooth transformation $\mathbf{h} : E^{\mathrm{c}} \to \mathbb{R}^n$:

$$W^{\mathrm{c}} = \big\{\mathbf{x} \mid \mathbf{x} = \mathbf{z} + \mathbf{h}(\mathbf{z})\big\}. \tag{3}$$

The geometrical interpretation of this parameterization of the center manifold is illustrated in Fig. 1.

The flow in W^{c} defined by (1) is determined through (3) by solutions to the differential equation in $\mathbf{z} \in E^{\mathrm{c}}$

$$\Big(\mathbf{I} + \frac{\partial \mathbf{h}}{\partial \mathbf{z}}\Big)\cdot\dot{\mathbf{z}} = \mathbf{J}\cdot\mathbf{z} + \mathbf{J}\cdot\mathbf{h}(\mathbf{z}) + \mathbf{f}\big(\mathbf{z} + \mathbf{h}(\mathbf{z})\big), \tag{4}$$

in which $\mathbf{I}$ is the unit tensor. Equation (4) may be transformed to the differential equation

$$\dot{\mathbf{z}} = \Big(\mathbf{I} + \frac{\partial \mathbf{h}}{\partial \mathbf{z}}\Big)^{-1}\cdot\Big(\mathbf{J}\cdot\mathbf{z} + \mathbf{J}\cdot\mathbf{h}(\mathbf{z}) + \mathbf{f}\big(\mathbf{z} + \mathbf{h}(\mathbf{z})\big)\Big) \tag{5}$$

which we formally express as

$$\dot{\mathbf{z}} = \mathbf{J}\cdot\mathbf{z} + \mathbf{g}(\mathbf{z}), \tag{6}$$

with the nonlinear part $\mathbf{g}(\mathbf{z})$ still to be determined.

We now represent the vector $\mathbf{z} \in E^{\mathrm{c}}$ by coordinates $z_1, \ldots, z_r$ in the basis of critical eigenvectors

$$\mathbf{z} = \sum_{j=1}^{r} z_j \mathbf{u}_j. \tag{7}$$

We can then Taylor expand the relevant functions defined on E^{c} in the coordinates z_j as follows

$$\mathbf{f}\big(\mathbf{z} + \mathbf{h}(\mathbf{z})\big) = \sum_{\mathbf{p}} \mathbf{f}_{\mathbf{p}} \mathbf{z}^{\mathbf{p}}, \tag{8a}$$

$$\mathbf{h}(\mathbf{z}) = \sum_{\mathbf{p}} \mathbf{h}_{\mathbf{p}} \mathbf{z}^{\mathbf{p}}, \tag{8b}$$

$$\mathbf{g}(\mathbf{z}) = \sum_{\mathbf{p}} \mathbf{g}_{\mathbf{p}} \mathbf{z}^{\mathbf{p}}. \tag{8c}$$

Here

$$\mathbf{p} = (p_1, \ldots, p_r) \in \mathbb{N}_0^r, \tag{9a}$$

$$\mathbf{z}^{\mathbf{p}} = \prod_{j=1}^{r} z_j^{p_j}, \tag{9b}$$

and $|\mathbf{p}| = \sum_{j=1}^{r} p_j \geq 2$ for all terms of the nonlinear functions defined in (8). The coefficients $\mathbf{f}_{\mathbf{p}}$, $\mathbf{h}_{\mathbf{p}}$, and $\mathbf{g}_{\mathbf{p}}$ are vectors in $\mathbb{R}^n$ ($\mathbb{C}^n$ if any of the critical eigenvalues are complex). In terms of the particular coordinates z_j, the set of differential equations from (6) for the flow on the center manifold W^{c} becomes

$$\dot{z}_j = \lambda_j z_j + \sum_{\mathbf{p}} (\mathbf{u}_j^* \cdot \mathbf{g}_{\mathbf{p}}) \mathbf{z}^{\mathbf{p}}, \tag{10}$$

which we shall refer to as the *amplitude equation* for (1) on the center manifold when the transformation $\mathbf{h}(\mathbf{z})$ is chosen so that (10) contains as few non-vanishing coefficients $\mathbf{u}_j^* \cdot \mathbf{g}_{\mathbf{p}}$ as possible. As described below, this procedure also defines the transformation $\mathbf{h}(\mathbf{z})$.

The transformation $\mathbf{h}(\mathbf{z})$ is determined through its coefficients $\mathbf{h}_{\mathbf{p}}$ in (8b) which must be obtained iteratively together with the coefficients $\mathbf{f}_{\mathbf{p}}$ and $\mathbf{g}_{\mathbf{p}}$. This is possible because the center subspace E^{c} is tangent to the center manifold W^{c} at $\mathbf{x} = \mathbf{0}$. We therefore substitute (6) and (8) in (4) to get

$$\begin{gathered}\Big(\mathbf{I} + \sum_{\mathbf{p}} \sum_{j=1}^{r} \mathbf{h}_{\mathbf{p}} \mathbf{z}^{\mathbf{p}} \frac{p_j}{z_j} \mathbf{u}_j^*\Big) \cdot \Big(\sum_{k=1}^{r} z_k \lambda_k \mathbf{u}_k + \sum_{\mathbf{p}} \mathbf{g}_{\mathbf{p}} \mathbf{z}^{\mathbf{p}}\Big) = \\ \sum_{k=1}^{r} z_k \lambda_k \mathbf{u}_k + \mathbf{J} \cdot \sum_{\mathbf{p}} \mathbf{h}_{\mathbf{p}} \mathbf{z}^{\mathbf{p}} + \sum_{\mathbf{p}} \mathbf{f}_{\mathbf{p}} \mathbf{z}^{\mathbf{p}}.\end{gathered} \tag{11}$$

The equation for the linear terms has already been anticipated in (6). For the nonlinear terms, (11) must be satisfied for each term indicated by $\mathbf{p}$ separately. We shall introduce a notation for the coefficient to $\mathbf{z}^{\mathbf{p}}$ from the product of the two sums over $\mathbf{p}$ on the left taken together with the last term on the right-hand side of (11), namely

$$\mathbf{\Phi}_{\mathbf{p}} = \mathbf{f}_{\mathbf{p}} - \sum_{\mathbf{p}'} \mathbf{h}_{\mathbf{p}'} \sum_{j=1}^{r} p'_j \mathbf{u}_j^* \cdot \mathbf{g}_{(\mathbf{p} - \mathbf{p}' + \boldsymbol{\delta}_j)}. \tag{12}$$

Here the sum over $\mathbf{p}'$ is taken over all ordered sets $\mathbf{p}' = (p'_1, \ldots, p'_r)$ for which the terms are defined, whereas the set $\boldsymbol{\delta}_j$ has δ_{jk} as its k'th component.

From (11), we then get the coefficient $\mathbf{g}_\mathbf{p}$ as

$$\mathbf{g}_\mathbf{p} = \Big(\mathbf{J} - \sum_{j=1}^{r} p_j \lambda_j \mathbf{I}\Big)\cdot\mathbf{h}_\mathbf{p} + \boldsymbol{\Phi}_\mathbf{p}. \tag{13}$$

Thus, the coefficient $\mathbf{g}_\mathbf{p}$ can be eliminated if the coefficient $\mathbf{h}_\mathbf{p}$ of the transformation $\mathbf{h}(\mathbf{z})$ can be chosen in such a way that the right-hand side of (13) is zero, that is if

$$\Big(\mathbf{J} - \sum_{j=1}^{r} p_j \lambda_j \mathbf{I}\Big)\cdot\mathbf{h}_\mathbf{p} = -\boldsymbol{\Phi}_\mathbf{p}, \tag{14}$$

is solvable for $\mathbf{h}_\mathbf{p}$. By biorthogonality, (14) splits into two independent equations for components in E^{c} and components in the generalized eigenspace complement to E^{c}. In the complement subspace, (14) can always be satisfied. For components in E^{c}, (14) can be solved for any component $\mathbf{u}_i^*\cdot\mathbf{h}_\mathbf{p}$ of $\mathbf{h}_\mathbf{p}$ in the eigenvector basis $\mathbf{u}_i$ for which $\sum_{j=1}^{r} p_j\lambda_j \neq \lambda_i$. For each of these components, we may eliminate the corresponding term $\mathbf{u}_i^*\cdot\mathbf{g}_\mathbf{p}$ of (10) by choosing $\mathbf{u}_i^*\cdot\mathbf{h}_\mathbf{p}$ as the solution to (14), namely

$$\mathbf{u}_i^*\cdot\mathbf{h}_\mathbf{p} = \frac{-\mathbf{u}_i^*\cdot\boldsymbol{\Phi}_\mathbf{p}}{\lambda_i - \sum_{j=1}^{r} p_j\lambda_j}. \tag{15}$$

In contrast, a component $\mathbf{u}_i^*\cdot\mathbf{g}_\mathbf{p}$ of $\mathbf{g}_\mathbf{p}$ cannot be eliminated by any choice of transformation $\mathbf{h}(\mathbf{z})$ if the resonance condition

$$\sum_{j=1}^{r} p_j\lambda_j = \lambda_i \tag{16}$$

applies. The condition (16) is identical to the one appearing in a somewhat different setting in the traditional derivation of the normal form theorem [16, 17], and the essential contents are of course the same in the two descriptions. The resonant terms must appear in the amplitude equation (10) and are determined by (13) once the corresponding components $\mathbf{u}_i^*\cdot\mathbf{h}_\mathbf{p}$ of the transformation $\mathbf{h}(\mathbf{z})$ have been chosen. We set each of them equal to zero so any non-vanishing (resonant) coefficient becomes (from (13))

$$\mathbf{u}_i^*\cdot\mathbf{g}_\mathbf{p} = \mathbf{u}_i^*\cdot\boldsymbol{\Phi}_\mathbf{p}. \tag{17}$$

The amplitude equation can now be written more explicitly as

$$\dot{z}_i = \lambda_i z_i + \sum_{\mathbf{p}} (\mathbf{u}_i^*\cdot\boldsymbol{\Phi}_\mathbf{p})\mathbf{z}^\mathbf{p}, \quad i = 1, \ldots, p, \tag{18}$$

in which the sum for the i'th amplitude z_i is taken over all sets $\mathbf{p}$ that satisfy the resonance condition (16).

In practice, calculation of the amplitude equation (18) does not require a decomposition of (14) as we did above. For any given $\mathbf{p}$, we may solve (14) directly for all non-resonant components of $\mathbf{h}_\mathbf{p}$ in terms of the part of $\boldsymbol{\Phi}_\mathbf{p}$ biorthogonal to the null space of $(\mathbf{J} - \sum_{j=1}^{r} p_j\lambda_j\mathbf{I})$, so $\mathbf{h}_\mathbf{p}$ is completely determined by the set of equations

$$\Big(\mathbf{J} - \sum_{j=1}^{r} p_j \lambda_j \mathbf{I}\Big)\cdot\mathbf{h}_\mathbf{p} = -\mathbf{Q}_\mathbf{p}\cdot\boldsymbol{\Phi}_\mathbf{p}, \tag{19a}$$

$$\mathbf{R}_\mathbf{p}\cdot\mathbf{h}_\mathbf{p} = \mathbf{0}. \tag{19b}$$

Here the projections $\mathbf{R}_{\mathbf{p}}$ and $\mathbf{Q}_{\mathbf{p}}$ are defined for any $\mathbf{x} \in \mathbb{R}^n$ as

$$\mathbf{R}_{\mathbf{p}} \cdot \mathbf{x} = (\mathbf{I} - \mathbf{Q}_{\mathbf{p}}) \cdot \mathbf{x} = \sum_i (\mathbf{u}_i^* \cdot \mathbf{x}) \mathbf{u}_i, \tag{20}$$

where the sum is taken over all integers i for which the resonance condition (16) is satisfied at given order $\mathbf{p}$. In practice, the solution of (19) is conveniently obtained by means of singular value decomposition [18].

We shall refer to the transformation $\mathbf{x} = \mathbf{z} + \mathbf{h}(\mathbf{z})$ from E^{c} to W^{c} with $\mathbf{h}(\mathbf{z})$ determined by (8b) and (19) as the *amplitude transformation* associated with the (1).

The problem of finding the non-vanishing coefficients of the amplitude equation (18) and the coefficients $\mathbf{h}_{\mathbf{p}}$ of the amplitude transformation leading to it, is solved order by order for increasing $|\mathbf{p}| = \sum_{j=1}^{r} p_j$. For any given $\mathbf{p}$ with $|\mathbf{p}| \geq 2$, the non-vanishing components of the vector coefficient $\mathbf{g}_{\mathbf{p}}$ of the amplitude equation are determined by the *resonant part* of $\mathbf{\Phi}_{\mathbf{p}}$ whereas $\mathbf{h}_{\mathbf{p}}$ is obtained as the solution to (19) in terms of the *non-resonant part* of $\mathbf{\Phi}_{\mathbf{p}}$. We note that, for any $\mathbf{p}, i$, either $\mathbf{u}_i^* \cdot \mathbf{g}_{\mathbf{p}}$ or $\mathbf{u}_i^* \cdot \mathbf{h}_{\mathbf{p}}$ must vanish.

The iterative solution is possible because $\mathbf{\Phi}_{\mathbf{p}}$ is determined by lower order coefficients of $\mathbf{g}_{\mathbf{p}}$ and $\mathbf{h}_{\mathbf{p}}$. This fact is obvious since the sum over $\mathbf{p}'$ in (12) only involves coefficients of orders within the range $2 \leq \mathbf{p}' \leq |\mathbf{p}| - 1$, and since the Taylor expansion of $\mathbf{f}(\mathbf{x})$ contains no linear terms. Consequently, the first term, $\mathbf{f}_{\mathbf{p}}$, on the right-hand side of (12) only contains components $\mathbf{h}_{\mathbf{p}'}$ of orders $2, \ldots, |\mathbf{p}| - 1$ through (8a).

The amplitude equation (18) and the linear system of equations (19) together with expression (12) for $\mathbf{\Phi}_{\mathbf{p}}$, constitute the main result of this section. Their practical use for a number of specific bifurcations will be demonstrated in Section 5. First we need to extend the theory to systems defined at a finite distance from the bifurcation point. This we do next.

3 Unfoldings of amplitude equations

For physical systems, one is often interested in studying the behavior of a dynamical system in a vicinity of a certain bifurcation point. We therefore consider a dynamical system

$$\dot{\mathbf{x}} = \mathbf{F}(\mathbf{x}, \boldsymbol{\mu}) = \mathbf{J} \cdot \mathbf{x} + \mathbf{f}(\mathbf{x}, \boldsymbol{\mu}), \tag{21}$$

depending on a set of parameters $\boldsymbol{\mu} \in \mathbb{R}^s$, in such a way that it contains the system (1) considered previously as the special case $\boldsymbol{\mu} = \mathbf{0}$. In physical problems, the motion in a "slow manifold" at $\boldsymbol{\mu} \neq \mathbf{0}$ smoothly developed from the center manifold at $\boldsymbol{\mu} = \mathbf{0}$, is of special importance. There are several ways of approaching this problem. One may treat the motion in an unstable manifold in the same way as described in the (previous) Section 2 for the center manifold with but a minor modification. We shall comment on this idea in Section 7.

Here we use an approach described in [9] and extend the differential equation (21) as

$$\begin{aligned} \dot{\mathbf{x}} &= \mathbf{J} \cdot \mathbf{x} + \mathbf{f}(\mathbf{x}, \boldsymbol{\mu}), \\ \dot{\boldsymbol{\mu}} &= \mathbf{0}, \end{aligned} \tag{22}$$

in which $(\mathbf{x}, \boldsymbol{\mu}) \in \mathbb{R}^{n+s}$. Note that we treat the term $\mathbf{J} \cdot \mathbf{x}$ linear in $\mathbf{x}$ explicitly in (22) whereas all other terms are contained in $\mathbf{f}(\mathbf{x}, \boldsymbol{\mu})$.

We are interested in the motion in the center manifold of the extended system (22), which represents the slow motion for finite $\boldsymbol{\mu}$ near $\boldsymbol{\mu} = \mathbf{0}$, desired for an efficient description of the physical problem. Unfortunately, we cannot use the results of Section 2 directly because the linear part of the vector field in (22) need not have $r + s$ independent critical eigenvectors. Nevertheless, the structure of (22) is so simple that we can use essentially the same approach as in Section 2. We sketch the arguments and introduce the necessary notation in order to analyze the extended system.

We consider only a dependence of the vector field on the parameter $\boldsymbol{\mu}$ for which $(\mathbf{0}, \boldsymbol{\mu}) \in \mathbb{R}^{n+s}$ belongs to the center subspace of (22) at $(\mathbf{x}, \boldsymbol{\mu}) = (\mathbf{0}, \mathbf{0})$. Then the center manifold of (22) may be parameterized by points $(\mathbf{z}, \boldsymbol{\mu}) \in E^{\mathrm{c}} \times \mathbb{R}^s$ in the center subspace of the extended system through a transformation $\mathbf{h} : \mathbb{R}^n \times \mathbb{R}^s \to \mathbb{R}^n$:

$$W^{\mathrm{c}} = \bigl\{(\mathbf{x}, \boldsymbol{\mu}) \bigm| \mathbf{x} = \mathbf{z} + \mathbf{h}(\mathbf{z}, \boldsymbol{\mu})\bigr\}. \tag{23}$$

This means that the flow in W^{c} defined by (22) is determined by the differential equation

$$\begin{aligned} \dot{\mathbf{z}} &= \Bigl(\mathbf{I} + \frac{\partial \mathbf{h}}{\partial \mathbf{z}}\Bigr)^{-1} \cdot \Bigl(\mathbf{J}\cdot\mathbf{z} + \mathbf{J}\cdot\mathbf{h}(\mathbf{z}, \boldsymbol{\mu})) + \mathbf{f}\bigl(\mathbf{z} + \mathbf{h}(\mathbf{z}, \boldsymbol{\mu}), \boldsymbol{\mu}\bigr)\Bigr), \\ \dot{\boldsymbol{\mu}} &= \mathbf{0}. \end{aligned} \tag{24}$$

Clearly, this differential equation can be written in the form

$$\dot{\mathbf{z}} = \mathbf{J}\cdot\mathbf{z} + \mathbf{g}(\mathbf{z}, \boldsymbol{\mu}). \tag{25}$$

We express $\mathbf{z}$ in a basis of eigenvectors of $\mathbf{J}$ as $\mathbf{z} = \sum_{j=1}^{r} z_j \mathbf{u}_j$, and expand the functions $\mathbf{f}$, $\mathbf{h}$, and $\mathbf{g}$ in a manner similar to (8) as

$$\mathbf{f}\bigl(\mathbf{z} + \mathbf{h}(\mathbf{z}, \boldsymbol{\mu}), \boldsymbol{\mu}\bigr) = \sum_{\mathbf{pq}} \mathbf{f}_{\mathbf{pq}} \mathbf{z}^{\mathbf{p}} \boldsymbol{\mu}^{\mathbf{q}}, \tag{26a}$$

$$\mathbf{h}(\mathbf{z}, \boldsymbol{\mu}) = \sum_{\mathbf{pq}} \mathbf{h}_{\mathbf{pq}} \mathbf{z}^{\mathbf{p}} \boldsymbol{\mu}^{\mathbf{q}}, \tag{26b}$$

$$\mathbf{g}(\mathbf{z}, \boldsymbol{\mu}) = \sum_{\mathbf{pq}} \mathbf{g}_{\mathbf{pq}} \mathbf{z}^{\mathbf{p}} \boldsymbol{\mu}^{\mathbf{q}}, \tag{26c}$$

in which

$$\mathbf{p} = (p_1, \ldots, p_r) \in \mathbb{N}_0^r, \quad \mathbf{q} = (q_1, \ldots, q_s) \in \mathbb{N}_0^s, \tag{27a}$$

$$\mathbf{z}^{\mathbf{p}} = \prod_{j=1}^{r} z_j^{p_j}, \quad \boldsymbol{\mu}^{\mathbf{q}} = \prod_{k=1}^{s} \mu_k^{q_k}. \tag{27b}$$

Note that we have introduced the short-hand notation $\mathbf{pq}$ for the index $(\mathbf{p}, \mathbf{q})$. Here, $|\mathbf{p}| + |\mathbf{q}| \geq 1$, with the cases $|\mathbf{p}| = 1$, $|\mathbf{q}| = 0$ excluded. Since (23)–(26) each has the same structure as in section 2, we arrive at the following equation for the vector $\mathbf{g}_{\mathbf{pq}}$ which must be satisfied for each separate order $(\mathbf{p}, \mathbf{q})$

$$\mathbf{g}_{\mathbf{pq}} = \Bigl(\mathbf{J} - \sum_{j=1}^{r} p_j \lambda_j \mathbf{I}\Bigr) \cdot \mathbf{h}_{\mathbf{pq}} + \boldsymbol{\Phi}_{\mathbf{pq}}. \tag{28}$$

The vector $\boldsymbol{\Phi}_{\mathbf{pq}} \in \mathbb{R}^n$ is defined by a straightforward extension of (12), namely

$$\boldsymbol{\Phi}_{\mathbf{pq}} = \mathbf{f}_{\mathbf{pq}} - \sum_{\mathbf{p}'\mathbf{q}'} \mathbf{h}_{\mathbf{p}'\mathbf{q}'} \sum_{j=1}^{r} p'_j \mathbf{u}_j^* \cdot \mathbf{g}_{(\mathbf{p}-\mathbf{p}'+\boldsymbol{\delta}_j)(\mathbf{q}-\mathbf{q}')}. \tag{29}$$

Consequently, the vector $\mathbf{g}_{\mathbf{pq}}$ will vanish provided that $\mathbf{h}_{\mathbf{pq}}$ is chosen as a solution to the equation

$$\Big(\mathbf{J} - \sum_{j=1}^{r} p_j\lambda_j\mathbf{I}\Big)\cdot\mathbf{h}_{\mathbf{pq}} = -\mathbf{Q}_{\mathbf{p}}\cdot\boldsymbol{\Phi}_{\mathbf{pq}}, \tag{30a}$$

$$\mathbf{R}_{\mathbf{p}}\cdot\mathbf{h}_{\mathbf{pq}} = \mathbf{0}. \tag{30b}$$

Observe now that (30) has exactly the same form as (19). We may therefore conclude that the unfolding of the amplitude equation in (18) simply becomes

$$\dot{z}_i = \lambda_i z_i + \sum_{\mathbf{pq}}(\mathbf{u}_i^*\cdot\boldsymbol{\Phi}_{\mathbf{pq}})\mathbf{z}^{\mathbf{p}}\boldsymbol{\mu}^{\mathbf{q}}, \quad i = 1,\dots,p, \tag{31}$$

where the sum for the i'th component is taken over all sets $(\mathbf{p},\mathbf{q})$ where resonance occurs. For $\boldsymbol{\mu} = \mathbf{0}$, only terms with $|\mathbf{q}| = 0$ contribute, and we recover the results of the previous section. For general $\boldsymbol{\mu}$, (31) is an extension of (18) which incorporates the parametric dependence on $\boldsymbol{\mu}$ of the resonant terms.

Equations (28) and (29) thus constitute a recurrence relation for determining $\mathbf{g}_{pq}$ and $\mathbf{h}_{pq}$. One must first determine the coefficients for $|\mathbf{q}| = 0$ for all orders $\mathbf{p}$ up to p_0+1 where p_0 is the maximum value of $|\mathbf{p}|$ to be included for any $\mathbf{q}$. Subsequently, the coefficients are determined for all q with $|\mathbf{q}| = 1$ in the same way.

On the center manifold, the functions $\mathbf{g}(\mathbf{z},\boldsymbol{\mu})$ and $\mathbf{h}(\mathbf{z},\boldsymbol{\mu})$ are at least quadratic in $\mathbf{z}$. However, the unfoldings may contain nonvanishing coefficients $\mathbf{g}_{pq}$ and $\mathbf{h}_{pq}$ with $|\mathbf{p}| = 0, 1$ when $|\mathbf{q}| \geq 1$. In other words, the functions $\mathbf{g}(\mathbf{z},\boldsymbol{\mu})$ and $\mathbf{h}(\mathbf{z},\boldsymbol{\mu})$ may contain terms depending on $\boldsymbol{\mu}$ which are constant or linear in $\mathbf{z}$ which now briefly discuss. For $|\mathbf{p}| = 0$ and $|\mathbf{q}| = 1$, we have

$$\mathbf{J}\cdot\mathbf{h}_{\mathbf{0}\boldsymbol{\delta}_k} = -\mathbf{Q}_{\mathbf{0}}\cdot\boldsymbol{\Phi}_{\mathbf{0}\boldsymbol{\delta}_k}, \quad \text{for} \quad k = 1,\dots,q. \tag{32}$$

with $\boldsymbol{\delta}_k$ defined below (12). If $\lambda_i \neq 0$, the corresponding coefficient $\mathbf{u}_i^*\cdot\mathbf{g}_{\mathbf{0}\boldsymbol{\delta}_k}$ will vanish from the amplitude equation provided that the coefficient $\mathbf{u}_i^*\cdot\mathbf{h}_{\mathbf{0}\boldsymbol{\delta}_k}$ is chosen as

$$\mathbf{u}_i^*\cdot\mathbf{h}_{\mathbf{0}\boldsymbol{\delta}_k} = -\frac{\mathbf{u}_i^*\cdot\boldsymbol{\Phi}_{\mathbf{0}\boldsymbol{\delta}_k}}{\lambda_i}. \tag{33}$$

On the other hand, if $\lambda_i = 0$ we choose $\mathbf{u}_i^*\cdot\mathbf{h}_{\mathbf{0}\boldsymbol{\delta}_k} = 0$ by (30b), and get the following contribution from $\mathbf{u}_i^*\cdot\mathbf{g}_{\mathbf{0}\boldsymbol{\delta}_k}$ in the amplitude equation

$$\mathbf{u}_i^*\cdot\mathbf{g}_{\mathbf{0}\boldsymbol{\delta}_k} = \mathbf{u}_i^*\cdot\boldsymbol{\Phi}_{\mathbf{0}\boldsymbol{\delta}_k}. \tag{34}$$

At the order $|\mathbf{p}| = 1$, $|\mathbf{q}| = 1$, we find that the following equation must hold for each ordered pair $(\boldsymbol{\delta}_j, \boldsymbol{\delta}_k)$

$$(\mathbf{J} - \lambda_j\mathbf{I})\cdot\mathbf{h}_{\boldsymbol{\delta}_j\boldsymbol{\delta}_k} = -\mathbf{Q}_{\boldsymbol{\delta}_j}\cdot\boldsymbol{\Phi}_{\boldsymbol{\delta}_j\boldsymbol{\delta}_k}. \tag{35}$$

For $i = j$, we always have $\mathbf{u}_j^*\cdot(\mathbf{J} - \lambda_j\mathbf{I})\cdot\mathbf{h}_{\boldsymbol{\delta}_j\boldsymbol{\delta}_k} = 0$, implying that we get a contribution to the amplitude equation given by $\mathbf{u}_j^*\cdot\mathbf{g}_{\boldsymbol{\delta}_j\boldsymbol{\delta}_k} = \mathbf{u}_j^*\cdot\boldsymbol{\Phi}_{\boldsymbol{\delta}_j\boldsymbol{\delta}_k}$ and $\mathbf{u}_j^*\cdot\mathbf{h}_{\boldsymbol{\delta}_j\boldsymbol{\delta}_k} = 0$ from (30b). In the asymmetric case $i \neq j$ we have

$$\lambda_i \neq \lambda_j : \qquad \mathbf{u}_i^*\cdot\mathbf{h}_{\boldsymbol{\delta}_j\boldsymbol{\delta}_k} = -\frac{\mathbf{u}_i^*\cdot\boldsymbol{\Phi}_{\boldsymbol{\delta}_j\boldsymbol{\delta}_k}}{\lambda_i - \lambda_j}, \qquad \mathbf{u}_i^*\cdot\mathbf{g}_{\boldsymbol{\delta}_j\boldsymbol{\delta}_k} = 0, \tag{36a}$$

$$\lambda_i = \lambda_j : \qquad \mathbf{u}_i^*\cdot\mathbf{h}_{\boldsymbol{\delta}_j\boldsymbol{\delta}_k} = 0, \qquad \mathbf{u}_i^*\cdot\mathbf{g}_{\boldsymbol{\delta}_j\boldsymbol{\delta}_k} = \mathbf{u}_i^*\cdot\boldsymbol{\Phi}_{\boldsymbol{\delta}_j\boldsymbol{\delta}_k}. \tag{36b}$$

We shall illustrate the use of these results in Section 5 and explain their meaning in Section 7.

4 Amplitude equations for iterated maps

The description of the dynamics on center manifolds for iterated maps is very similar to that of flows presented in Section 2. Therefore we merely give a short outline of the theory.

A discrete system in $\mathbb{R}^n$ is described by a map of the form

$$\mathbf{x} \mapsto \mathbf{F}(\mathbf{x}) = \mathbf{J}\cdot\mathbf{x} + \mathbf{f}(\mathbf{x}). \tag{37}$$

We assume that $\mathbf{x} = \mathbf{0}$ is a non-hyperbolic fixed point of (37) where the linear part $\mathbf{J}$ has r eigenvalues λ_j with $|\lambda_j| = 1$ $(j = 1, \ldots, r)$. The corresponding right and left eigenvectors are denoted by $\mathbf{u}_j$ and $\mathbf{u}_j^*$ and are assumed to be normalized in accordance with the biorthonormal relations in (2). The r-dimensional center manifold W^{c} of the fixed point $\mathbf{x} = \mathbf{0}$ may be parameterized by points in the center subspace as

$$\mathbf{x} = \mathbf{z} + \mathbf{h}(\mathbf{z}) \equiv \mathbf{K}(\mathbf{z}), \tag{38}$$

where $\mathbf{x} \in W^{\mathrm{c}}$ and $\mathbf{z} \in E^{\mathrm{c}}$. Inserting (38) into (37) yields

$$\mathbf{z} + \mathbf{h}(\mathbf{z}) \mapsto \mathbf{J}\cdot\mathbf{z} + \mathbf{J}\cdot\mathbf{h}(\mathbf{z}) + \mathbf{f}\big(\mathbf{z} + \mathbf{h}(\mathbf{z})\big), \tag{39}$$

which shows that the discrete dynamics on the center manifold is induced by the map

$$\mathbf{z} \mapsto \mathbf{K}^{-1}\Big(\mathbf{J}\cdot\mathbf{z} + \mathbf{J}\cdot\mathbf{h}(\mathbf{z}) + \mathbf{f}\big(\mathbf{z} + \mathbf{h}(\mathbf{z})\big)\Big), \tag{40}$$

in the center subspace.

To find the map in E^{c} explicitly, we formally express it as

$$\mathbf{z} \mapsto \mathbf{J}\cdot\mathbf{z} + \mathbf{g}(\mathbf{z}). \tag{41}$$

As in the continuous case, we express $\mathbf{z}$ in terms of coordinates based on the right eigenvectors $\mathbf{u}_j$, *viz.* $\mathbf{z} = \sum_{j=1}^r z_j \mathbf{u}_j$. The functions $\mathbf{f}\big(\mathbf{z} + \mathbf{h}(\mathbf{z})\big)$, $\mathbf{h}(\mathbf{z})$, and $\mathbf{g}(\mathbf{z})$ can then be Taylor expanded as

$$\mathbf{f}\big(\mathbf{z} + \mathbf{h}(\mathbf{z})\big) = \sum_{\mathbf{p}} \mathbf{f}_{\mathbf{p}} \mathbf{z}^{\mathbf{p}}, \tag{42a}$$

$$\mathbf{h}(\mathbf{z}) = \sum_{\mathbf{p}} \mathbf{h}_{\mathbf{p}} \mathbf{z}^{\mathbf{p}}, \tag{42b}$$

$$\mathbf{g}(\mathbf{z}) = \sum_{\mathbf{p}} \mathbf{g}_{\mathbf{p}} \mathbf{z}^{\mathbf{p}}, \tag{42c}$$

and the map (41) becomes

$$z_i \mapsto \lambda_i z_i + \sum_{\mathbf{p}} (\mathbf{u}_i^*\cdot\mathbf{g}_{\mathbf{p}})\mathbf{z}^{\mathbf{p}}. \tag{43}$$

When the transformation $\mathbf{h}(\mathbf{z})$ is chosen so that (43) contains as few non-vanishing coefficients $\mathbf{u}_j^*\cdot\mathbf{g}_{\mathbf{p}}$ as possible, we shall refer to this equation as the amplitude equation for the map in (37).

To determine $\mathbf{h}(\mathbf{z})$, we first substitute (41) for $\mathbf{z}$ on the left-hand side of (39). Since the resulting expression is equal to the right-hand side of (39), we obtain

$$\mathbf{J}\cdot\mathbf{z} + \mathbf{g}(\mathbf{z}) + \mathbf{h}\big(\mathbf{J}\cdot\mathbf{z} + \mathbf{g}(\mathbf{z})\big) = \mathbf{J}\cdot\mathbf{z} + \mathbf{J}\cdot\mathbf{h}(\mathbf{z}) + \mathbf{f}\big(\mathbf{z} + \mathbf{h}(\mathbf{z})\big). \tag{44}$$

Here we note that the term $\mathbf{h}\big(\mathbf{J}\cdot\mathbf{z}+\mathbf{g}(\mathbf{z})\big)$ may be written as

$$\begin{aligned}\mathbf{h}\big(\mathbf{J}\cdot\mathbf{z}+\mathbf{g}(\mathbf{z})\big) &= \sum_{\mathbf{p}} \mathbf{h}_{\mathbf{p}} \prod_{j=1}^{r} \big(\lambda_j z_j + \sum_{\mathbf{p}'} (\mathbf{u}_j^{*}\cdot\mathbf{g}_{\mathbf{p}'})\mathbf{z}^{\mathbf{p}'}\big)^{p_j}, \\ &= \sum_{\mathbf{p}} \mathbf{h}_{\mathbf{p}}\mathbf{z}^{\mathbf{p}} \prod_{j=1}^{r} \lambda_j^{p_j} + \sum_{\mathbf{p}} \mathbf{\Psi}_{\mathbf{p}}\mathbf{z}^{\mathbf{p}}. \end{aligned} \tag{45}$$

The last step defines the vector $\mathbf{\Psi}_{\mathbf{p}} \in \mathbb{R}^n$ which abbreviates the (rather complicated) coefficient that remains at order $\mathbf{p}$ when the term $\sum_{\mathbf{p}} \mathbf{h}_{\mathbf{p}}\mathbf{z}^{\mathbf{p}} \prod_{j=1}^{r} \lambda_j^{p_j}$ is taken out. Substitution of $\mathbf{z} = \sum_{j=1}^{r} z_j \mathbf{u}_j$ together with (42), and (45) in (44) followed by a simple rearrangement of terms then yields the following expression for the coefficient vector $\mathbf{g}_{\mathbf{p}}$

$$\mathbf{g}_{\mathbf{p}} = \Big(\mathbf{J} - \prod_{j=1}^{r} \lambda_j^{p_j}\mathbf{I}\Big)\cdot\mathbf{h}_{\mathbf{p}} + \mathbf{\Phi}_{\mathbf{p}}, \tag{46}$$

where $\mathbf{\Phi}_{\mathbf{p}} = \mathbf{f}_{\mathbf{p}} - \mathbf{\Psi}_{\mathbf{p}}$. Consequently, the coefficient vector $\mathbf{g}_{\mathbf{p}}$ can be eliminated if $\mathbf{h}_{\mathbf{p}}$ is chosen as a solution to the equation

$$\big(\mathbf{J} - \prod_{j=1}^{r} \lambda_j^{p_j}\mathbf{I}\big)\cdot\mathbf{h}_{\mathbf{p}} = -\mathbf{\Phi}_{\mathbf{p}}. \tag{47}$$

However, a component $\mathbf{u}_i^{*}\cdot\mathbf{g}_{\mathbf{p}}$ of $\mathbf{g}_{\mathbf{p}}$ cannot be removed by any choice of $\mathbf{h}_{\mathbf{p}}$ if the resonance condition

$$\prod_{j=1}^{r} \lambda_j^{p_j} = \lambda_i, \tag{48}$$

is satisfied.

Using a series of arguments analogous to the derivation of the amplitude equation for flows given in section 2, one easily obtains the following recurrence relation for the coefficients $\mathbf{g}_{\mathbf{p}}$ and $\mathbf{h}_{\mathbf{p}}$ of the amplitude equation and the associated transformation

$$\mathbf{g}_{\mathbf{p}} = \Big(\mathbf{J} - \prod_{j=1}^{r} \lambda_j^{p_j}\mathbf{I}\Big)\cdot\mathbf{h}_{\mathbf{p}} + \mathbf{\Phi}_{\mathbf{p}}. \tag{49}$$

We may therefore conclude that the unfolding of the amplitude equation (43) becomes

$$z_i \mapsto \lambda_i z_i + \sum_{\mathbf{p}} (\mathbf{u}_i^{*}\cdot\mathbf{\Phi}_{\mathbf{p}})\mathbf{z}^{\mathbf{p}}, \quad i = 1,\dots,p, \tag{50}$$

where the sum is taken over all resonant sets $\mathbf{p}$ for the i'th component. Furthermore, all resonant components $\mathbf{u}_i^{*}\cdot\mathbf{h}_{\mathbf{p}}$ of $\mathbf{h}_{\mathbf{p}}$ are set equal to zero whereas non-resonant terms are removed by choosing the corresponding coefficient $\mathbf{u}_i\cdot\mathbf{h}_{\mathbf{p}}$ of $\mathbf{h}_{\mathbf{p}}$ as

$$\mathbf{u}_i^{*}\cdot\mathbf{h}_{\mathbf{p}} = \frac{-\mathbf{u}_i^{*}\cdot\mathbf{\Phi}_{\mathbf{p}}}{\lambda_i - \prod_{j=1}^{r} \lambda_j^{p_j}}. \tag{51}$$

Again, we note that the resonance condition (48) is identical to the one that appears in the traditional normal form derivation for diffeomorphisms [16, 17].

For a map depending on a set of parameters $\boldsymbol{\mu} \in \mathbb{R}^s$,

$$\mathbf{x} \mapsto \mathbf{F}(\mathbf{x}, \boldsymbol{\mu}) = \mathbf{J}\cdot\mathbf{x} + \mathbf{f}(\mathbf{x}, \boldsymbol{\mu}), \tag{52}$$

we use the same approach as for flows and study the extended system

$$\begin{aligned} \mathbf{x} &\mapsto \mathbf{J}\cdot\mathbf{x} + \mathbf{f}(\mathbf{x}, \boldsymbol{\mu}), \\ \boldsymbol{\mu} &\mapsto \boldsymbol{\mu}. \end{aligned} \tag{53}$$

Using expansions (26) and an approach completely analogous to the one discussed above, we find a recurrence relation

$$\mathbf{g}_{\mathbf{pq}} = \Big(\mathbf{J} - \prod_{j=1}^{r} \lambda_j^{p_j} \mathbf{I}\Big)\cdot\mathbf{h}_{\mathbf{pq}} + \boldsymbol{\Phi}_{\mathbf{pq}}. \tag{54}$$

with $\boldsymbol{\Phi}_{pq} = \mathbf{f}_{pq} - \boldsymbol{\Psi}_{pq}$ where the definition of $\boldsymbol{\Psi}_{pq}$ is analogous to that of $\boldsymbol{\Psi}_p$. An example of the calculation of $\boldsymbol{\Phi}_{pq}$ for the period doubling bifurcation in Section 5.5 illustrates the use of the formula. In conclusion, the unfolded amplitude equation for the iterated map (53) becomes

$$z_i \mapsto \lambda_i z_i + \sum_{\mathbf{pq}} (\mathbf{u}_i^* \cdot \boldsymbol{\Phi}_{\mathbf{pq}}) \mathbf{z}^{\mathbf{p}} \boldsymbol{\mu}^{\mathbf{q}}, \quad i = 1, \dots, r, \tag{55}$$

where the sum is taken over all sets $(\mathbf{p}, \mathbf{q})$ for which resonance occurs for the i'th component.

The coefficients $\mathbf{h}_{\mathbf{pq}}$ of the unfolded amplitude transformation are determined as solutions to the linear equations

$$(\mathbf{J} - \prod_{j=1}^{r} \lambda_j^{p_j} \mathbf{I})\cdot\mathbf{h}_{\mathbf{pq}} = -\mathbf{Q}_{\mathbf{p}}\cdot\boldsymbol{\Phi}_{\mathbf{pq}}, \tag{56a}$$

$$\mathbf{R}_{\mathbf{p}}\cdot\mathbf{h}_{\mathbf{pq}} = \mathbf{0}. \tag{56b}$$

As for (19), the linear system (56) is solved in practice by application of a singular value decomposition.

In Section 5.5 below, we demonstrate the use of these results for the period doubling bifurcation.

5 Amplitude equations for simple bifurcations

In this section, we derive explicit expressions for the coefficients of the amplitude equation and the associated transformation $\mathbf{h}(\mathbf{z}, \boldsymbol{\mu})$ to lowest non-trivial order for some simple bifurcations. For this purpose, we represent the vector field on the right-hand side of (21) and (52) as Taylor expansions in some physically relevant coordinates x_j of $\mathbf{x} \in \mathbb{R}^n$ and μ_j of $\boldsymbol{\mu} \in \mathbb{R}^s$. In terms of $\mathbf{x}$ and $\boldsymbol{\mu}$ the expansion of the vector field (21) takes the form

$$\mathbf{F}(\mathbf{x}, \boldsymbol{\mu}) = \mathbf{J}\cdot\mathbf{x} + \mathbf{F}_{\boldsymbol{\mu}}\cdot\boldsymbol{\mu} + \mathbf{F}_{\mathbf{x}\boldsymbol{\mu}}(\mathbf{x}, \boldsymbol{\mu}) + \tfrac{1}{2!}\mathbf{F}_{\mathbf{xx}}(\mathbf{x}, \mathbf{x}) + \tfrac{1}{3!}\mathbf{F}_{\mathbf{xxx}}(\mathbf{x}, \mathbf{x}, \mathbf{x}) + \cdots, \tag{57}$$

in concise notation with

$$\begin{aligned} \mathbf{F}_{\mathbf{xx}}(\mathbf{x}, \mathbf{x}) &= \sum_{i,j=1}^{n} \frac{\partial^2 \mathbf{F}}{\partial x_i \partial x_j} x_i x_j, \qquad \mathbf{F}_{\mathbf{xxx}}(\mathbf{x}, \mathbf{x}, \mathbf{x}) = \sum_{i,j,k=1}^{n} \frac{\partial^3 \mathbf{F}}{\partial x_i \partial x_j \partial x_k} x_i x_j x_k, \\ \mathbf{F}_{\boldsymbol{\mu}}\cdot\boldsymbol{\mu} &= \sum_{i=1}^{s} \frac{\partial \mathbf{F}}{\partial \mu_i} \mu_i, \qquad \mathbf{F}_{\mathbf{x}\boldsymbol{\mu}}(\mathbf{x}, \boldsymbol{\mu}) = \sum_{i=1}^{n} \sum_{j=1}^{s} \frac{\partial^2 \mathbf{F}}{\partial x_i \partial \mu_j} x_i \mu_j, \ \dots \end{aligned} \tag{58}$$

where all derivatives are evaluated at $\mathbf{x} = \mathbf{0}$ and $\boldsymbol{\mu} = \mathbf{0}$. Here, the multilinear vector functions, $\mathbf{F}_{\mathbf{xx}}(\mathbf{x},\mathbf{x})$, $\mathbf{F}_{\mathbf{xxx}}(\mathbf{x},\mathbf{x},\mathbf{x})$, *etc*, are symmetric in all their arguments, so we need not specify them any further. We shall only consider unfoldings linear in $\boldsymbol{\mu}$, so we need not take any terms beyond those exhibited in (57) into account. From part of (57) nonlinear in $\mathbf{x}$, namely

$$\mathbf{f}(\mathbf{x},\boldsymbol{\mu}) = \mathbf{F}_{\boldsymbol{\mu}}\cdot\boldsymbol{\mu} + \mathbf{F}_{\mathbf{x}\boldsymbol{\mu}}(\mathbf{x},\boldsymbol{\mu}) + \tfrac{1}{2!}\mathbf{F}_{\mathbf{xx}}(\mathbf{x},\mathbf{x}) + \tfrac{1}{3!}\mathbf{F}_{\mathbf{xxx}}(\mathbf{x},\mathbf{x},\mathbf{x}) + \cdots, \tag{59}$$

we get the coefficients $\mathbf{f}_{\mathbf{pq}}$ by first substituting the parameterization of the center manifold

$$\mathbf{x} = \sum_{j=1}^{r} z_j \mathbf{u}_j + \sum_{\mathbf{pq}} \mathbf{h}_{\mathbf{pq}} \mathbf{z}^{\mathbf{p}} \boldsymbol{\mu}^{\mathbf{q}} \tag{60}$$

for $\mathbf{x}$ and then collecting all terms of order $(\mathbf{p},\mathbf{q})$ (*i.e.* terms containing $\mathbf{z}^{\mathbf{p}}\boldsymbol{\mu}^{\mathbf{q}}$). In the examples considered here, we shall only discuss problems associated with a scalar parametric dependence μ, implying that we may simplify the multilinear vector functions in (57) by writing

$$\mathbf{F}_{\mathbf{x}^p\mu^q}(\mathbf{x},\mathbf{x},\ldots,\mathbf{x},\mu,\mu,\ldots,\mu) = \mathbf{F}_{\mathbf{x}^p\mu^q}(\mathbf{x},\mathbf{x},\ldots,\mathbf{x})\mu^q. \tag{61}$$

5.1 Bifurcations at a single zero eigenvalue

We first look at a stationary point of the flow (1) where one real eigenvalue of $\mathbf{J}$ is zero and assume that all other eigenvalues have non-zero real parts. We denote the right and left eigenvectors corresponding to $\lambda = 0$ by $\mathbf{u}$ and $\mathbf{u}^*$ respectively. Here the center manifold and the center subspace are both one-dimensional, and the latter is spanned by $\mathbf{u}$. There is just one amplitude z, and the set of integers $\mathbf{p}$ becomes just a simple index p.

The resonance condition (16) takes the form $\lambda = p\lambda$, and is satisfied for all orders $p \geq 2$. So none of the nonlinear terms of the amplitude equation vanish in general, whereas all of the components $\mathbf{u}^*\cdot\mathbf{h}_{pq}$ do. At the bifurcation point, the amplitude equation (31) therefore has the following form

$$\dot{z} = g_{01}\mu + g_{11}\mu z + g_{20}z^2 + g_{30}z^3 + \cdots, \tag{62}$$

in which $g_{pq} = \mathbf{u}^*\cdot\mathbf{g}_{pq}$. For the lowest order contributions to the amplitude equation and the transformation $\mathbf{h}(\mathbf{z},\mu)$, we need first calculate $\boldsymbol{\Phi}_{pq}$ from (29). To obtain the coefficients $\mathbf{f}_{pq}$, we substitute

$$\mathbf{x} = \mathbf{u}z + \mathbf{h}_{01}\mu + \mathbf{h}_{11}\mu z + \mathbf{h}_{20}z^2 + \mathbf{h}_{30}z^3 + \cdots \tag{63}$$

in the expansion (59)

$$\begin{aligned}\mathbf{f}(\mathbf{x}) = \mathbf{F}_{\mu}\mu + \big(\mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{01})\big)\mu z +{}& \\ \tfrac{1}{2}\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{u})z^2 + \big(\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{20}) + \tfrac{1}{6}\mathbf{F}_{\mathbf{xxx}}(\mathbf{u},\mathbf{u},\mathbf{u})\big)z^3 + \cdots.&\end{aligned} \tag{64}$$

Thus,

$$\mathbf{f}_{01} = \mathbf{F}_{\mu}, \tag{65a}$$

$$\mathbf{f}_{11} = \mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{01}), \tag{65b}$$

$$\mathbf{f}_{20} = \tfrac{1}{2}\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{u}), \tag{65c}$$

$$\mathbf{f}_{30} = \mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{20}) + \tfrac{1}{6}\mathbf{F}_{\mathbf{xxx}}(\mathbf{u},\mathbf{u},\mathbf{u}). \tag{65d}$$

Second order in z ($p = 2$ and $q = 0$)
At second order, there is no contribution from the sum over p' and q' in (29), implying that

$$\boldsymbol{\Phi}_{20} = \mathbf{f}_{20} = \tfrac{1}{2}\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{u}). \tag{66}$$

We therefore get the second order coefficient of the amplitude equation from (31) as

$$g_{20} = \mathbf{u}^* \cdot \mathbf{\Phi}_{20} = \tfrac{1}{2}\mathbf{u}^* \cdot \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{u}), \tag{67}$$

and a linear equation for the coefficient vector $\mathbf{h}_{20}$ from (30)

$$\mathbf{J} \cdot \mathbf{h}_{20} = -\tfrac{1}{2}\mathbf{Q} \cdot \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{u}), \tag{68a}$$

$$\mathbf{u}^* \cdot \mathbf{h}_{20} = 0, \tag{68b}$$

with the projection $\mathbf{Q}$ defined through $\mathbf{Q} \cdot \mathbf{x} = \mathbf{x} - (\mathbf{u}^* \cdot \mathbf{x})\mathbf{u}$.

Third order in z ($p = 3$ and $q = 0$)

Once $\mathbf{g}_{20}$ and $\mathbf{h}_{20}$ have been obtained from (67) and (68) respectively, we may derive the third order contributions using (29) for $\mathbf{\Phi}_{30}$

$$\begin{aligned} \mathbf{\Phi}_{30} &= \mathbf{f}_{30} - 2g_{20}\mathbf{h}_{20}, \\ &= \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{20}) + \tfrac{1}{6}\mathbf{F}_{\mathbf{xxx}}(\mathbf{u}, \mathbf{u}, \mathbf{u}) - 2g_{20}\mathbf{h}_{20}. \end{aligned} \tag{69}$$

We observe that $\mathbf{u}^* \cdot \mathbf{h}_{20} = 0$, and conclude from the above expression that

$$g_{30} = \mathbf{u}^* \cdot \mathbf{\Phi}_{30} = \mathbf{u}^* \cdot \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{20}) + \tfrac{1}{6}\mathbf{u}^* \cdot \mathbf{F}_{\mathbf{xxx}}(\mathbf{u}, \mathbf{u}, \mathbf{u}), \tag{70}$$

whereas the coefficient vector $\mathbf{h}_{30}$ is determined by the linear equation

$$\mathbf{J} \cdot \mathbf{h}_{30} = -\mathbf{Q} \cdot \big(\mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{20}) + \tfrac{1}{6}\mathbf{F}_{\mathbf{xxx}}(\mathbf{u}, \mathbf{u}, \mathbf{u})\big) + 2g_{20}\mathbf{h}_{20}, \tag{71a}$$

$$\mathbf{u}^* \cdot \mathbf{h}_{30} = 0. \tag{71b}$$

Following this procedure, the iterative solution for g_{p0} and $\mathbf{h}_{p0}$ can be developed to still higher orders.

Unfolding terms ($p = 0$ and $q = 1$)

Here $\mathbf{\Phi}_{01} = \mathbf{f}_{01}$. From (65), we get the first contribution to the unfolding as

$$g_{01} = \mathbf{u}^* \cdot \mathbf{F}_{\mu}. \tag{72}$$

In order to find $\mathbf{h}_{01}$, we must solve the linear equations

$$\mathbf{J} \cdot \mathbf{h}_{01} = -\mathbf{Q} \cdot \mathbf{F}_{\mu}, \tag{73a}$$

$$\mathbf{u}^* \cdot \mathbf{h}_{01} = 0. \tag{73b}$$

Unfolding terms ($p = 1$ and $q = 1$)

From (29), we find that $\mathbf{\Phi}_{11} = \mathbf{f}_{11} - 2g_{01}\mathbf{h}_{20}$. Having obtained both g_{01} and $\mathbf{h}_{01}$, we may finally find the contribution g_{11} to the unfolding of the amplitude equation (62) as

$$g_{11} = \mathbf{u}^* \cdot \mathbf{\Phi}_{11} = \mathbf{u}^* \cdot \mathbf{F}_{\mathbf{x}\mu} \cdot \mathbf{u} + \mathbf{u}^* \cdot \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{01}), \tag{74}$$

since $\mathbf{u}^* \cdot \mathbf{h}_{20} = 0$. The coefficient vector $\mathbf{h}_{11}$ can then be obtained by solving the linear system of equations

$$\mathbf{J} \cdot \mathbf{h}_{11} = -\mathbf{Q}\big(\cdot \mathbf{F}_{\mathbf{x}\mu} \cdot \mathbf{u} + \cdot \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{01})\big) - 2g_{01}\mathbf{h}_{20}, \tag{75a}$$

$$\mathbf{u}^* \cdot \mathbf{h}_{11} = 0. \tag{75b}$$

We now specialize the results for the amplitude equation to three important bifurcations at a single zero eigenvalue, including only the terms at lowest order in z for $q = 0, 1$. For the terms linear in μ, we introduce the simpler notation $\sigma_p = g_{p1}$, whereas we shall use $g_p = g_{p0}$ for terms independent of μ.

5.1.1 Saddle-node bifurcation

If $\sigma_0 \neq 0$ and $g_2 \neq 0$, a saddle-node bifurcation occurs at $\mu = 0$, and the corresponding amplitude equations takes the form

$$\dot{z} = \sigma_0 \mu + g_2 z^2, \tag{76}$$

with

$$g_2 = \tfrac{1}{2}\mathbf{u}^* \cdot \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{u}), \tag{77a}$$

$$\sigma_0 = \mathbf{u}^* \cdot \mathbf{F}_\mu. \tag{77b}$$

5.1.2 Transcritical bifurcation

If $\sigma_0 = 0$ but $\sigma_1 \neq 0$ and $g_2 \neq 0$, a transcritical bifurcation occurs at $\mu = 0$, for which the amplitude equation is

$$\dot{z} = \sigma_1 \mu z + g_2 z^2, \tag{78}$$

with g_2 given by (77a) and

$$\sigma_1 = \mathbf{u}^* \cdot \mathbf{F}_{\mathbf{x}\mu} \cdot \mathbf{u} + \mathbf{u}^* \cdot \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{01}). \tag{79}$$

5.1.3 Pitchfork bifurcation

Finally, if $\sigma_0 = 0$ and $g_2 = 0$, but $\sigma_1 \neq 0$ and $g_3 \neq 0$, a pitchfork bifurcation is realized at $\mu = 0$. Here the amplitude equation becomes

$$\dot{z} = \sigma_1 \mu z + g_3 z^3, \tag{80}$$

where σ_1 is given by (79) and

$$g_3 = \mathbf{u}^* \cdot \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{20}) + \tfrac{1}{6}\mathbf{u}^* \cdot \mathbf{F}_{\mathbf{xxx}}(\mathbf{u}, \mathbf{u}, \mathbf{u}). \tag{81}$$

The results derived for these three bifurcations are summarized in Table 1, which also exhibits the equations for the coefficients of the amplitude transformation.

5.2 Bifurcations at $\lambda = 1$ for iterated maps

The results derived above for flows require little modification in order to give the coefficients of the equivalent amplitude equations for saddle-node, transcritical, and pitchfork bifurcations in the iterated map (37) (at a fixed point where one eigenvalue of $\mathbf{J}$ satisfies $\lambda = 1$ and all other eigenvalues have $\lambda \neq 1$). In fact, the only necessary modification is to

$$\textit{replace } \mathbf{J} \textit{ by } \mathbf{J} - \mathbf{I} \tag{82}$$

everywhere in (68), (71), (73), and (75). For this reason, we do not show the details of the calculations for the iterated map here, but simply give the results for the unfolded amplitude equations:

$$z \mapsto \sigma_0 \mu + z + g_2 z^2 \qquad (\textit{saddle-node}), \tag{83a}$$

$$z \mapsto (1 + \sigma_1 \mu) z + g_2 z^2 \qquad (\textit{transcritical}), \tag{83b}$$

$$z \mapsto (1 + \sigma_1 \mu) z + g_3 z^3 \qquad (\textit{pitchfork}). \tag{83c}$$

Here the coefficients σ_0, σ_1, g_2, and g_3 are given by (77b), (79), (77a), and (81) with the linear equations (68), (71), (73), and (75) modified in accordance with (82). The results derived for the saddle-node, the transcritical, and pitchfork bifurcations for iterated maps are summarized in Table 1.

5.3 Hopf bifurcation

We now consider a stationary point of the flow (21) at which the linearization $\mathbf{J}$ has two complex conjugate, pure imaginary eigenvalues $\lambda_1 = \overline{\lambda}_2 = \mathrm{i}\,\omega_0$, and all other eigenvalues have non-zero real parts. We denote the right and left eigenvectors of $\mathbf{J}$ corresponding to λ_1 by $\mathbf{u}_1$ and $\mathbf{u}_1^*$, and those of λ_2 by $\mathbf{u}_2$ and $\mathbf{u}_2^*$, as in the general theory — and choose $\mathbf{u}_2 = \overline{\mathbf{u}}_1$ normalized according to (2). Consequently, we may simplify the notation by defining $\mathbf{u} = \mathbf{u}_1$ and $\mathbf{u}^* = \mathbf{u}_1^*$. By this choice, the two-dimensional center subspace is spanned by any linear combinations of $\mathrm{Re}\,\mathbf{u}$ and $\mathrm{Im}\,\mathbf{u}$, whereas the motion in the two-dimensional center manifold is determined by an amplitude equation which, as a straightforward application of the general theory, is formulated in terms of the two complex eigenvalues and complex conjugate amplitudes $z, \overline{z}$ with $\mathbf{z} = z\mathbf{u} + \overline{z}\overline{\mathbf{u}} \in E^{\mathrm{c}}$.

The ordered set of integers $\mathbf{p}$ now has two components, $\mathbf{p} = (p_1, p_2)$. The resonance condition for any $\mathbf{p}$ is satisfied for either of the two components if

$$p_1\lambda_1 + p_2\lambda_2 = (p_1 - p_2)\lambda_1 = \lambda_1 \tag{84a}$$

or

$$p_1\lambda_1 + p_2\lambda_2 = (p_2 - p_1)\lambda_2 = \lambda_2. \tag{84b}$$

Thus, the resonance condition is fulfilled for the first component if $p_1 = p_2 + 1$, and for the second component if $p_2 = p_1 + 1$ provided that $p_1 + p_2 \geq 2$. The amplitude equation therefore takes the form

$$\dot{z} = \mathrm{i}\,\omega_0 z + g_{101}\mu z + g_{210}|z|^2 z + g_{320}|z|^4 z + \cdots, \tag{85}$$

where $g_{ijk} = \mathbf{u}^*\!\cdot\mathbf{g}_{ijk}$.

To derive expressions for the coefficients of (85), we first determine the constant vectors $\mathbf{f}_{\mathbf{pq}}$ by substitution of

$$\mathbf{x} = \mathbf{u}z + \overline{\mathbf{u}z} + \mathbf{h}_{200}z^2 + \mathbf{h}_{110}|z|^2 + \mathbf{h}_{020}\overline{z}^2 + \mathbf{h}_{001}\mu + \mathbf{h}_{101}\mu z + \mathbf{h}_{011}\mu\overline{z} + \cdots \tag{86}$$

in (59). Collecting separate orders in z, $\overline{z}$, and μ, we find the following contributions for terms of zero order in μ

$$\mathbf{f}_{200} = \tfrac{1}{2}\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{u}), \tag{87a}$$

$$\mathbf{f}_{110} = \mathbf{F}_{\mathbf{xx}}(\mathbf{u},\overline{\mathbf{u}}), \tag{87b}$$

$$\mathbf{f}_{300} = \mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{200}) + \tfrac{1}{6}\mathbf{F}_{\mathbf{xxx}}(\mathbf{u},\mathbf{u},\mathbf{u}), \tag{87c}$$

$$\mathbf{f}_{210} = \mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{110}) + \mathbf{F}_{\mathbf{xx}}(\overline{\mathbf{u}},\mathbf{h}_{200}) + \tfrac{1}{2}\mathbf{F}_{\mathbf{xxx}}(\mathbf{u},\mathbf{u},\overline{\mathbf{u}}). \tag{87d}$$

whereas the terms linear in μ are

$$\mathbf{f}_{001} = \mathbf{F}_{\mu}, \tag{88a}$$

$$\mathbf{f}_{101} = \mathbf{F}_{\mathbf{x}\mu}\!\cdot\mathbf{u} + \mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{001}), \tag{88b}$$

Notice also that $\mathbf{\Phi}_{\mathbf{p}0} = \mathbf{f}_{\mathbf{p}0}$ at second and third orders in $|\mathbf{p}|$ because the first non-vanishing coefficients $\mathbf{g}_{\mathbf{p}0}$ come at third order in $|\mathbf{p}|$. Although all second order coefficients $\mathbf{g}_{\mathbf{p}0}$ vanish, we must still derive the coefficients $\mathbf{h}_{\mathbf{p}0}$ of the transformation $\mathbf{h}$ at second order since these are needed to obtain the higher order coefficients $\mathbf{g}_{\mathbf{p}0}$ as well as for determining the amplitude transformation.

Second order terms in z ($p_1 + p_2 = 2$ and $q = 0$)
From (87), we find

$$\mathbf{\Phi}_{200} = \overline{\mathbf{\Phi}}_{020} = \tfrac{1}{2}\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{u}), \tag{89a}$$

$$\mathbf{\Phi}_{110} = \mathbf{F}_{\mathbf{xx}}(\mathbf{u},\overline{\mathbf{u}}). \tag{89b}$$

Since there is no resonance at second order, the right-hand side of (30a) is simply $-\mathbf{\Phi}_{\mathbf{p}0}$, and we get using $\lambda_1 = \overline{\lambda}_2 = \mathrm{i}\,\omega_0$

$$(\mathbf{J} - 2\,\mathrm{i}\,\omega_0\mathbf{I})\cdot\mathbf{h}_{200} = -\tfrac{1}{2}\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{u}), \tag{90a}$$

$$\mathbf{J}\cdot\mathbf{h}_{110} = -\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\overline{\mathbf{u}}), \tag{90b}$$

whereas $\mathbf{h}_{020}$ is determined by the relation $\mathbf{h}_{020} = \overline{\mathbf{h}}_{200}$.

Third order terms in z ($p_1 + p_2 = 3$ and $q = 0$)
Once (90) has been solved for the second order coefficient vectors $\mathbf{h}_{\mathbf{p}0}$, we immediately get the third order terms $\mathbf{\Phi}_{\mathbf{p}0}$ explicitly from (87)

$$\mathbf{\Phi}_{300} = \mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{200}) + \tfrac{1}{6}\mathbf{F}_{\mathbf{xxx}}(\mathbf{u},\mathbf{u},\mathbf{u}), \tag{91a}$$

$$\mathbf{\Phi}_{210} = \mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{110}) + \mathbf{F}_{\mathbf{xx}}(\overline{\mathbf{u}},\mathbf{h}_{200}) + \tfrac{1}{2}\mathbf{F}_{\mathbf{xxx}}(\mathbf{u},\mathbf{u},\overline{\mathbf{u}}), \tag{91b}$$

$$\mathbf{\Phi}_{120} = \overline{\mathbf{\Phi}}_{210}, \quad \mathbf{\Phi}_{030} = \overline{\mathbf{\Phi}}_{300}. \tag{91c}$$

The third order nonlinear coefficient g_{210} of the amplitude equation (85) then becomes

$$g_{210} = \mathbf{u}^*\cdot\mathbf{\Phi}_{210} = \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{110}) + \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\overline{\mathbf{u}},\mathbf{h}_{200}) + \tfrac{1}{2}\mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xxx}}(\mathbf{u},\mathbf{u},\overline{\mathbf{u}}). \tag{92}$$

Notice that expressions like (91) for $\mathbf{\Phi}_{\mathbf{p}0}$ can be written down immediately in terms of the coefficients $\mathbf{h}_{\mathbf{p}0}$ and $\mathbf{g}_{\mathbf{p}0}$, but to get explicit expressions, equations like (90) must first be solved for the lower order coefficients. In other words — to get explicit expressions, one must work order by order starting with the second order.

For the amplitude equation (85) to third order, we need go no further. However, to obtain an explicit expression for the transformation $\mathbf{h}(\mathbf{z})$ to third order we must solve the linear equations

$$(\mathbf{J} - 3\,\mathrm{i}\,\omega_0\mathbf{I})\cdot\mathbf{h}_{300} = -\mathbf{\Phi}_{300}, \tag{93a}$$

$$(\mathbf{J} - \mathrm{i}\,\omega_0\mathbf{I})\cdot\mathbf{h}_{210} = -\mathbf{Q}\cdot\mathbf{\Phi}_{210}, \tag{93b}$$

$$\mathbf{u}^*\cdot\mathbf{h}_{210} = 0, \tag{93c}$$

$$\mathbf{h}_{030} = \overline{\mathbf{h}}_{300}, \quad \mathbf{h}_{120} = \overline{\mathbf{h}}_{210}, \tag{93d}$$

where the projection $\mathbf{Q}$ is defined as

$$\mathbf{Q}\cdot\mathbf{x} = \mathbf{x} - (\mathbf{u}^*\cdot\mathbf{x})\mathbf{u}. \tag{94}$$

Unfolding terms ($p_1 = p_2 = 0$ and $q = 1$)
First, the coefficient vector $\mathbf{h}_{001}$, must be found by solving the linear equation

$$\mathbf{J}\cdot\mathbf{h}_{001} = -\mathbf{F}_{\mu}, \tag{95}$$

which is non-singular since $\lambda_1 = \overline{\lambda}_2 = \mathrm{i}\,\omega_0 \neq 0$.

Unfolding terms ($p_1 = 1$, $p_2 = 0$ and $q = 1$)
We first calculate $\mathbf{\Phi}_{101}$ as

$$\mathbf{\Phi}_{101} = \mathbf{f}_{101} - 2\mathbf{h}_{200}(\mathbf{u}^*\cdot\mathbf{g}_{001}) - 2\mathbf{h}_{110}(\mathbf{u}^*\cdot\mathbf{g}_{001}) \tag{96}$$

$$= \mathbf{f}_{101} = \mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{001}), \tag{97}$$

since $\mathbf{g}_{001} = \mathbf{0}$. Having obtained $\mathbf{h}_{001}$, the first non-trivial coefficient of the unfolded amplitude equation becomes

$$g_{101} = \mathbf{u}^*\cdot\mathbf{\Phi}_{101} = \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{001}), \tag{98}$$

whereas the linear equation which determines the corresponding coefficient vector $\mathbf{h}_{101}$ in the transformation becomes

$$(\mathbf{J} - \mathrm{i}\,\omega_0\mathbf{I})\cdot\mathbf{h}_{101} = -\mathbf{Q}\cdot\mathbf{\Phi}_{101}, \tag{99a}$$

$$\mathbf{u}^*\cdot\mathbf{h}_{101} = 0, \tag{99b}$$

$$\mathbf{h}_{011} = \overline{\mathbf{h}}_{101}, \tag{99c}$$

We now simplify the notation using the fact that one index, $p = p_1 + p_2$ say, is sufficient to describe the resonant terms since $p_1 = (p+1)/2$ and $p_2 = (p-1)/2$ for the first component. Setting $\sigma_1 = g_{101}$ and $g_3 = g_{210}$, we finally conclude that the unfolded amplitude equation becomes

$$\dot{z} = (\mathrm{i}\,\omega_0 + \sigma_1\mu)z + g_3 z|z|^2, \tag{100}$$

with

$$g_3 = \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{110}) + \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\overline{\mathbf{u}}, \mathbf{h}_{200}) + \tfrac{1}{2}\mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xxx}}(\mathbf{u}, \mathbf{u}, \overline{\mathbf{u}}), \tag{101a}$$

$$\sigma_1 = \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{001}). \tag{101b}$$

The results derived for the Hopf bifurcation for flows are summarized in Table 2.

5.4 Neimark-Sacker bifurcation

The equivalent situation where an iterated map (37) exhibits a Neimark-Sacker bifurcation corresponds to a fixed point where two complex eigenvalues of $\mathbf{J}$ satisfy $\lambda_1 = \overline{\lambda}_2 = \mathrm{e}^{\mathrm{i}\theta_0}$ ($|\lambda_1| = |\lambda_2| = 1$). For simplicity, we exclude the strong resonance cases where $\theta_0 = \frac{2\pi}{k}$ for $k = 1$, 2, 3, or 4. The unfolded amplitude equation and the associated coefficients for this problem is easily obtained by only a few modifications of the results derived above for the Hopf bifurcation for flows. The only required modification is to

$$\textit{replace} \qquad (\mathbf{J} - \mathrm{i}\,k\omega_0\mathbf{I}) \qquad \textit{by} \qquad (\mathbf{J} - \mathrm{e}^{\mathrm{i}k\theta_0}\mathbf{I}) \tag{102}$$

everywhere in (90), (93), (95), and (99). We shall not show the details of the remaining calculations here but merely present the main result for the amplitude equation for the Neimark-Sacker bifurcation, namely

$$z \mapsto (\mathrm{e}^{\mathrm{i}\theta_0} + \sigma_1\mu)z + g_3 z|z|^2, \tag{103}$$

with the coefficients g_3 and σ_1 given by (101a) and (101b) respectively with the linear equations (90), (93), and (95) modified according to (102). The results for the amplitude equation for the Neimark-Sacker bifurcation are summarized in Table 2.

5.5 Period doubling bifurcation

To illustrate the principles of deriving amplitude equations for iterated maps, we consider a fixed point solution $\mathbf{x} = \mathbf{0}$ of (53) where one eigenvalue of $\mathbf{J}$ satisfies $\lambda = -1$ at $\mu = 0$ whereas all other eigenvalues are assumed to have modulus different from unity. The right and left eigenvectors are denoted by $\mathbf{u}$ and $\mathbf{u}^*$ respectively corresponding to a one-dimensional center manifold described by a single real amplitude z and a simple index p.

The resonance condition (48) is simply $\lambda = \lambda^p$, which is satisfied for all odd $p \geq 3$. Correspondingly, the amplitude equation (50) takes the form

$$z \mapsto (g_{11}\mu - 1)z + g_{30}z^3 + g_{50}z^5 + \cdots , \tag{104}$$

with $g_{pq} = \mathbf{u}^* \cdot \mathbf{g}_{pq}$.

To determine relations for the coefficients of (104), we first insert

$$\mathbf{x} = \mathbf{u}z + \mathbf{h}_{20}z^2 + \mathbf{h}_{30}z^3 + \mathbf{h}_{01}\mu + \mathbf{h}_{11}\mu z + \cdots \tag{105}$$

in (59) and find the following expressions for $\mathbf{f}_{20}$, $\mathbf{f}_{30}$, $\mathbf{f}_{01}$, and $\mathbf{f}_{11}$

$$\mathbf{f}_{20} = \tfrac{1}{2}\mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{u}), \tag{106a}$$
$$\mathbf{f}_{30} = \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{20}) + \tfrac{1}{6}\mathbf{F}_{\mathbf{xxx}}(\mathbf{u}, \mathbf{u}, \mathbf{u}), \tag{106b}$$
$$\mathbf{f}_{01} = \mathbf{F}_{\mu}, \tag{106c}$$
$$\mathbf{f}_{11} = \mathbf{F}_{\mathbf{x}\mu} \cdot \mathbf{u} + \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{01}). \tag{106d}$$

Now, to derive expressions for the constant vectors $\mathbf{\Phi}_{p0}$ defined implicitly by (44)–(54), we note that $\mathbf{u}^* \cdot \mathbf{g}_{20} = 0$, and conclude that $\mathbf{\Psi}_{p0} = \mathbf{0}$ for $p \leq 3$ since $\mathbf{u}^* \cdot \mathbf{g}_{p0}$ first enters (45) at fourth order. This therefore implies $\mathbf{\Phi}_{20} = \mathbf{f}_{20}$ and $\mathbf{\Phi}_{30} = \mathbf{f}_{30}$.

Second order terms in z ($p = 2$ and $q = 0$)
To find $\mathbf{h}_{20}$, we have

$$\mathbf{\Phi}_{20} = \tfrac{1}{2}\mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{u}). \tag{107}$$

There is no resonance at second order, but we must still solve the regular linear system

$$(\mathbf{J} - \mathbf{I}) \cdot \mathbf{h}_{20} = -\tfrac{1}{2}\mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{u}), \tag{108}$$

for $\mathbf{h}_{20}$ in order to obtain an explicit expression for $\mathbf{\Phi}_{30}$.

Third order terms in z ($p = 3$ and $q = 0$)
For $\mathbf{\Phi}_{30}$, we have

$$\mathbf{\Phi}_{30} = \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{20}) + \tfrac{1}{6}\mathbf{F}_{\mathbf{xxx}}(\mathbf{u}, \mathbf{u}, \mathbf{u}), \tag{109}$$

so once the linear equation for $\mathbf{h}_{20}$ has been solved, we may determine the resonant third order coefficient in (104) as

$$g_{30} = \mathbf{u}^* \cdot \mathbf{\Phi}_{30} = \mathbf{u}^* \cdot \big(\mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{20}) + \tfrac{1}{6}\mathbf{F}_{\mathbf{xxx}}(\mathbf{u}, \mathbf{u}, \mathbf{u})\big). \tag{110}$$

The third order term $\mathbf{h}_{30}$ of the transformation $\mathbf{h}(\mathbf{z})$ can then be found by solving the equations

$$(\mathbf{J} + \mathbf{I}) \cdot \mathbf{h}_{30} = -\mathbf{Q} \cdot \mathbf{\Phi}_{30}, \tag{111a}$$
$$\mathbf{u}^* \cdot \mathbf{h}_{30} = 0, \tag{111b}$$

where the projection $\mathbf{Q}$ is defined in (20), *i.e.* $\mathbf{Q}\cdot\mathbf{x} = \mathbf{x} - (\mathbf{u}^*\cdot\mathbf{x})\mathbf{u}$.

Unfolding terms ($p = 0, 1$ and $q = 1$)
To find $\boldsymbol{\Phi}_{01}$ and $\boldsymbol{\Phi}_{11}$, we use $\boldsymbol{\Phi}_{pq} = \mathbf{f}_{pq} - \boldsymbol{\Psi}_{pq}$ and take $\mathbf{f}_{pq}$ from (106). To determine any contribution from $\boldsymbol{\Psi}_{pq}$, we substitute the right-hand side of (104) for z in the expansion of $\mathbf{h}(z, \mu)$. Now, substract $\mathbf{h}(-z, \mu)$ and order the rest according to (p, q). The coefficient of $z^p\mu^q$ is then $\boldsymbol{\Phi}_{pq}$. We may than conclude for the period doubling bifurcation that $\boldsymbol{\Phi}_{01} = \boldsymbol{\Phi}_{11} = \mathbf{0}$. Consequently,

$$\boldsymbol{\Phi}_{01} = \mathbf{F}_{\mu}, \tag{112a}$$

$$\boldsymbol{\Phi}_{11} = \mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{01}). \tag{112b}$$

To determine the coefficient vector $\mathbf{h}_{01}$, we must solve the linear system

$$(\mathbf{J} - \mathbf{I})\cdot\mathbf{h}_{01} = -\mathbf{F}_{\mu}, \tag{113}$$

which always is regular since $\mathbf{J}$ by assumption has no eigenvalue $\lambda = 1$. Having obtained $\mathbf{h}_{01}$, we find the non-trivial contribution to the unfolding of the amplitude equation as

$$\mathbf{u}^*\cdot\mathbf{g}_{11} = \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{01}), \tag{114}$$

and the coefficient vector $\mathbf{h}_{11}$ by solving the linear system of equations

$$(\mathbf{J} + \mathbf{I})\cdot\mathbf{h}_{11} = -\mathbf{Q}\cdot\big(\mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{01})\big), \tag{115a}$$

$$\mathbf{u}^*\cdot\mathbf{h}_{11} = 0. \tag{115b}$$

In conclusion, we arrive at the following unfolded amplitude equation for the period doubling bifurcation

$$z \mapsto (\sigma_1\mu - 1)z + g_3 z^3, \tag{116}$$

where

$$g_3 = \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{20}) + \tfrac{1}{6}\mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xxx}}(\mathbf{u}, \mathbf{u}, \mathbf{u}), \tag{117}$$

$$\sigma_1 = \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{01}). \tag{118}$$

The results for the period doubling bifurcation are summarized in Table 3.

6 Scalings and proper amplitude equations

The amplitude of a harmonic oscillation is half the difference between the maximum and minimum values of the oscillating function. This basic concept of an amplitude can be generalized to a set of (possibly complex) Fourier amplitudes for anharmonic periodic oscillations. For the aperiodic (transient) oscillations that can occur near a Hopf bifurcation, we can introduce a slowly varying, complex amplitude w related to z of (100) by extracting the time dependence associated with harmonic oscillations with (vanishingly) small amplitude at the bifurcation point. Specifically, we can extract a phase factor $\mathrm{e}^{\mathrm{i}\omega_0 t}$ from $z(t)$ to get a time dependent amplitude modulating the "basic" oscillations described by the phase $\mathrm{e}^{\mathrm{i}\omega_0 t}$.

We shall introduce the notion of a "proper" amplitude to account for this and similar slow modulations. At the same time, it is convenient to account also for the important scalings characteristic of a Hopf bifurcation. Thus, the amplitude of the limit cycle oscillations grows as $\sqrt{\mu}$ for small μ, and the characteristic times in a vicinity of the stationary point as well as near the limit cycle are both proportional to μ close enough to the bifurcation point.

We therefore introduce a proper (scaled) amplitude $w(\tau)$ as a function of a scaled time τ by the definition

$$w(\tau) = \frac{1}{\sqrt{\mu}} \exp(-\,\mathrm{i}\,\omega_0 t) z(t), \tag{119}$$

$$\tau = \mu t. \tag{120}$$

Substitution of these two expressions in (100) then leads to the proper amplitude equation for $w(\tau)$

$$\frac{dw}{d\tau} = \sigma_1 w + g_3 w|w|^2, \tag{121}$$

which traditionally is called the Stuart-Landau equation [19, 20]. It has the important property of being independent of the distance from the bifurcation point (which of course only applies at the lowest non-trivial orders in z and μ of the original amplitude equation). So the Stuart-Landau equation is universal for any flow exhibiting a Hopf bifurcation — characterized by just two parameters σ_1 and g_3. Note that the scalings leading to (121) are dictated by the form of (100). The Stuart-Landau equation (121) can be derived from (100) without any knowledge of the properties of the Hopf bifurcation other than those contained in (100).

Our remarks leading to (121) are meant solely as motivation of the idea of scaling and are not needed for the derivation itself. On the contrary, we can infer the scaling properties for the limit cycle and the critical slowing down from the amplitude equation. This feature distinguishes the present derivation of (proper) amplitude equations from those based on multiple time scales; in the latter case the scalings are basic assumptions of the actual derivation of the amplitude equation whereas these follow naturally from the derivations presented here.

For non-oscillatory modes, the amplitude equations at lowest nonlinear order can also be scaled to yield a proper amplitude equation which also will be universal for any flow exhibiting the bifurcation in question. In fact, similar proper amplitude equations are easily derived for the saddle-node, the transcritical, and the pitchfork bifurcation. For the equivalent amplitude equations of an iterated map, one can show that the scaling $t = \mu\tau$ is replaced by an explicit factor μ in the scaled amplitude equation.

7 Interpretation of the unfoldings

The significance of the description of the motion in the center manifold in terms of an amplitude equation is obvious from the geometrical interpretation illustrated in Fig. 1. But the meaning of the unfolding is perhaps not so clear.

To understand terms like the coefficient vector $\mathbf{h}_{\mathbf{pq}}$ in (30) for $|\mathbf{q}| \neq 0$, we look first at the case $|\mathbf{p}| = 0$, $|\mathbf{q}| = 1$ corresponding to (32)–(34). These equations are associated with the change of the stationary point $\mathbf{x}_{\mathrm{s}}(\boldsymbol{\mu})$ with the parameter $\boldsymbol{\mu}$ as described by the equation

$$\mathbf{F}\big(\mathbf{x}_{\mathrm{s}}(\boldsymbol{\mu}), \boldsymbol{\mu}\big) = \mathbf{0}. \tag{122}$$

The change from $(\mathbf{x}_{\mathrm{s}}, \boldsymbol{\mu}) = (\mathbf{0}, \mathbf{0})$ is to first order in $\boldsymbol{\mu}$ determined by the equation

$$\frac{d\mathbf{F}}{d\boldsymbol{\mu}} \cdot \boldsymbol{\mu} = \big(\mathbf{J} \cdot \frac{\partial \mathbf{x}_{\mathrm{s}}}{\partial \boldsymbol{\mu}} + \mathbf{F}_{\mu}\big) \cdot \boldsymbol{\mu} = \mathbf{0} \tag{123}$$

in which all derivatives are evaluated at $(\mathbf{x}, \boldsymbol{\mu}) = (\mathbf{0}, \mathbf{0})$. For finite $\boldsymbol{\mu}$, the expression inside the parentheses in (123) must vanish, and we find

$$\mathbf{J} \cdot \frac{\partial \mathbf{x}_{\mathrm{s}}}{\partial \boldsymbol{\mu}} = -\mathbf{F}_{\mu}, \tag{124}$$

which corresponds to (32) for the k'th component of $\boldsymbol{\mu}$.

Thus the component of $\mathbf{h}_{\mathbf{0}\boldsymbol{\delta}_k}$ in the range of $\mathbf{J}$ determines the change in $\mathbb{R}^n$ of the stationary point $\mathbf{x}_{\mathrm{s}}(\boldsymbol{\mu})$ as

$$\mathbf{x}_{\mathrm{s}}(\boldsymbol{\mu}) = \sum_{k=1}^{s} \mathbf{h}_{\mathbf{0}\boldsymbol{\delta}_k} \mu_k. \tag{125}$$

A change with $\boldsymbol{\mu}$ of the motion in the nullspace of $\mathbf{J}$ is determined by the contribution to the amplitude equation (31) provided the derivative $\mathbf{F}_\mu$ has a non-vanishing component in the nullspace of $\mathbf{J}$. In contrast, the transformation $\mathbf{h}$ will have no component in the nullspace.

We see the effects of the $|\mathbf{p}| = 0$, $|\mathbf{q}| = 1$ contributions to the unfoldings for the single zero eigenvalue in Section 5.1 and for the Hopf bifurcation in Section 5.3. Thus, the change of the stationary point is given to first order in μ by (73) and (95). In this case, there is only a contribution to the amplitude equation for the saddle-node bifurcation where $\mathbf{F}_\mu$ has a non-vanishing component in the nullspace of $\mathbf{J}$. Here the non-hyperbolic stationary point splits in two which cannot be accounted for as a smooth displacement of the stationary point under the unfolding — a term must therefore appear in the amplitude equation. For the transcritical, pitchfork, and Hopf bifurcations, on the other hand, the change of the stationary point with μ can simply be accounted for by the smooth transformation $\mathbf{h}(\mathbf{z}, \boldsymbol{\mu})$.

At the order $|\mathbf{p}| = 1$, $|\mathbf{q}| = 1$ the unfolding can be understood in terms of perturbation theory for the eigenvalue problem. Consider the change of the Jacobian matrix at the stationary point $\mathbf{x}_{\mathrm{s}}$ to first order in $\boldsymbol{\mu}$

$$\mathbf{J}(\boldsymbol{\mu}) = \mathbf{J} + \mathbf{F}_{\mathbf{x}\boldsymbol{\mu}}(\cdot, \boldsymbol{\mu}) + \mathbf{F}_{\mathbf{x}\mathbf{x}}(\cdot, \mathbf{x}_{\mathrm{s}}), \tag{126}$$

in which $\mathbf{x}_{\mathrm{s}}$ (to first order in $\boldsymbol{\mu}$) is given by (125). For short we write (126) as

$$\mathbf{J}(\boldsymbol{\mu}) = \mathbf{J} + \delta\mathbf{J} \tag{127}$$

and consider the eigenvalue problem

$$(\mathbf{J} + \delta\mathbf{J})\cdot(\mathbf{u}_j + \delta\mathbf{u}_j) = (\lambda_j + \delta\lambda_j)(\mathbf{u}_j + \delta\mathbf{u}_j). \tag{128}$$

To lowest order (linear in $\boldsymbol{\mu}$), we find from perturbation theory [21] that the change $\delta\lambda_j$ of the eigenvalue λ_j is

$$\delta\lambda_j = \mathbf{u}_j^*\cdot\delta\mathbf{J}\cdot\mathbf{u}_j, \tag{129}$$

whereas the change $\delta\mathbf{u}_j$ of the eigenvector $\mathbf{u}_j$ is determined by the linear equation

$$\begin{aligned} (\mathbf{J} - \lambda_j\mathbf{I})\cdot\delta\mathbf{u}_j &= -(\mathbf{I} - \mathbf{u}_j\mathbf{u}_j^*)\cdot\delta\mathbf{J}\cdot\mathbf{u}_j, \\ \mathbf{u}_j^*\cdot\delta\mathbf{u}_j &= 0. \end{aligned} \tag{130}$$

From (126), we find for $\delta\mathbf{J}\cdot\mathbf{u}_j$

$$\delta\mathbf{J}\cdot\mathbf{u}_j = \mathbf{F}_{\mathbf{x}\mu}(\mathbf{u}_j, \boldsymbol{\mu}) + \mathbf{F}_{\mathbf{x}\mathbf{x}}(\mathbf{u}_j, \mathbf{x}_{\mathrm{s}}). \tag{131}$$

By comparison of (130) and (131) with (35), we identify $\mathbf{h}_{\boldsymbol{\delta}_j\boldsymbol{\delta}_k}$ as the contribution to the change of the j'th eigenvector per unit change of μ_k. Similarly, we identify the coefficient $\mathbf{u}_j^*\cdot\mathbf{g}_{\boldsymbol{\delta}_j\boldsymbol{\delta}_k}$ in the unfolded amplitude equation as the derivative of the j'th eigenvalue with respect to μ_k.

The effects of the $|\mathbf{p}| = 1$, $|\mathbf{q}| = 1$ contributions can be inferred directly from the specific bifurcations studied in Sections 5.1 and 5.3. For a scalar parameter μ, we have $\mathbf{\Phi}_{\boldsymbol{\delta}_j\boldsymbol{\delta}_k} = \mathbf{\Phi}_{\boldsymbol{\delta}_j 1}$ implying that (131) reduces to

$$\delta\mathbf{J}\cdot\mathbf{u}_j = \mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u}_j + \mathbf{F}_{\mathbf{xx}}(\mathbf{u}_j, \mathbf{h}_{\mathbf{01}}). \tag{132}$$

The right-hand side of this expression has the same form as (65b) and (88b) for a single zero eigenvalue and for a Hopf bifurcation respectively. For a scalar parameter, we also note that the change of the stationary point is simply $\mathbf{h}_{\mathbf{01}}\mu$ corresponding to first order terms $\mathbf{h}_{01}\mu$ and $\mathbf{h}_{001}\mu$ in Sections 5.1 and 5.3 respectively.

We can summarize these results for one critical component with eigenvalue λ, right eigenvector $\mathbf{u}$ and amplitude z in simplified notation (disregarding other critical modes) by grouping terms as follows

$$\dot{z} = g_{01}\mu + (\lambda + g_{11}\mu)z + \cdots\,, \tag{133a}$$

$$\mathbf{x} = \mathbf{h}_{01}\mu + (\mathbf{u} + \mathbf{h}_{11}\mu)z + \cdots\,, \tag{133b}$$

where '$\cdots$' indicates linear contributions from other critical components plus nonlinear terms.

Thus, the result (133) partly accounts for the change of the stationary point to $\mathbf{h}_{01}\mu$ and changed eigenvalue $\lambda + g_{11}\mu$ and eigenvector $\mathbf{u} + \mathbf{h}_{11}\mu$ evaluated at the new stationary point. It seems reasonably to assume that other terms can be interpreted as corrections changing the amplitude, but we shall not pursue the interpretation any further.

The interpretation indicated above suggest that for finite $\boldsymbol{\mu}$ one may obtain an efficient description of the dynamics by using the formulas obtained for the center manifold using the (nearly critical) eigenvalues and eigenvectors as well as all coefficients calculated from the vector field at $\mathbf{x}_{\mathrm{s}}(\boldsymbol{\mu})$ for the finite value of $\boldsymbol{\mu}$.

In the important special case where no eigenvalues have positive real parts at the bifurcation and all the critical eigenvalues and no others acquire positive real parts at the finite $\boldsymbol{\mu}$, we can appeal to the stable manifold theorem and use essentially the same line of reasoning as in Section 2 for the description of the motion in the unstable manifold. We may still classify the terms to include in the amplitude equation and those to include in the associated transformation according to whether or not the resonance condition is satisfied *at the bifurcation point*. Although it is in general possible to eliminate all nonlinear terms from the amplitude equation, one should not do so, but instead include precisely those that appear at the bifurcation. Then the amplitude equation and transformation change smoothly with $\boldsymbol{\mu}$, and the formulas derived here for the center manifold can be applied to the unstable manifold with all quantities calculated at $\mathbf{x}_{\mathrm{s}}(\boldsymbol{\mu})$ for finite $\boldsymbol{\mu}$.

8 Physical relevance of the amplitude equation

An amplitude equation describes the kind of dynamical behavior (*e.g.* chaos) that can be observed in any system to which it applies. It can therefore be studied in its own right as a representative of a large class of dynamical systems.

For a specific system, the amplitude equation has its coefficients fixed by the physical system. Some or all of these coefficients can often be determined from a summary knowledge of the system, such as characteristic (invariant) exponents. Furthermore, since the actual (physical) system is topologically equivalent to that determined by the amplitude equation, the number of solutions that branch off at the bifurcation point and the stability of the bifurcating solutions (the super- and subcritical nature of the bifurcation) are additional examples of characteristics that are determined directly by the properties of the amplitude equation.

However, to describe a real physical system in more detail in terms of amplitudes, the amplitude equation is not sufficient. The transformation (60) between the description in terms of amplitudes and the actual physical variables is essential. Fortunately, that transformation is obtained together with the amplitude equation with little extra work, since the coefficients $\mathbf{h}_{\mathbf{pq}}$ of the transformation must be calculated in order to determine the amplitude equation anyway.

For a given amplitude equation, we may therefore study the dynamics by either analytic or numerical methods and then use (60) to transform the dynamics back to the physical space of the original problem. For all the amplitude equations derived in Section 5, an analytic approach is possible. The calculation of the limit sets of these amplitude equations is straightforward. The results and their relation to the physical space is summarized in Tables 1–3 and Table 4 respectively.

The advantage of using an amplitude approach to a physical problem is that the essential dynamics usually takes place in a subspace (the center subspace of amplitudes) of much lower dimension than the full dimension of the dynamical system. So whether one has an experiment or a model, it is often advantageous to solve or analyze the problem in terms of amplitudes. For such work, a quantitative approach like that described in the present paper is necessary. As an example we mention a quantitative experimental analysis of oscillatory chemical reactions near a supercritical Hopf bifurcation relying on the Stuart-Landau equation (121) and the basic geometry of the amplitude transformation [22, 23] and a study of chemical waves in a complex chemical reaction-diffusion system [2].

9 Summary and discussion

The main result of this paper is a general and systematic method of deriving amplitude equations (or normal forms) for flows and iterated maps near a local bifurcation. In addition, the method also provides the transformations that connect the amplitude description with the "real world" described in terms of appropriate physical variables, the amplitude transformation. In particular, the method provides an explicit recurrence relation (28) with (29) for flows, and (54) for iterated maps in the case of semisimple critical eigenvalues.

The method is completely transparent: the amplitudes representing the instantaneous state of a system and the amplitude transformation to a physical description of the state have simple geometric interpretations. The use of the method for a given type of bifurcation is straightforward and unambiguous, and can in principle be carried out to any desired order of nonlinearity.

The method is efficient in terms of necessary computational efforts as will become clear from a summary of the steps of the method which we now present: We first have to find the eigenvalues λ_i and the associated eigenvectors $\mathbf{u}_i$ and $\mathbf{u}_i^*$ satisfying the condition $\operatorname{Re}\lambda_i = 0$ (for flows) or $|\lambda_i| = 1$ (for iterated maps). From this, we immediately get the structure of the amplitude equation and the amplitude transformation $\mathbf{h}(\mathbf{z}, \boldsymbol{\mu})$ through a classification of terms $\mathbf{u}_i^* \cdot \mathbf{g}_{\mathbf{pq}}$ and $\mathbf{u}_i^* \cdot \mathbf{h}_{\mathbf{pq}}$ depending on whether or not the resonance condition

$$\sum_{j=1}^{r} p_j \lambda_j = \lambda_i \qquad \text{(for flows)}, \tag{134a}$$

$$\prod_{j=1}^{r} \lambda_j^{p_j} = \lambda_i \qquad \text{(for maps)} \tag{134b}$$

is satisfied for the i'th component (amplitude z_i) of the term indicated by the order $(\mathbf{p}, \mathbf{q})$. The amplitude equation includes all resonant terms and no others, whereas the amplitude transformation contains non-resonant terms only.

The next step is to calculate the constant vectors $\boldsymbol{\Phi}_{\mathbf{pq}}$ in terms of the Taylor coefficients $\mathbf{f}_{\mathbf{pq}}$, $\mathbf{g}_{\mathbf{pq}}$, and $\mathbf{h}_{\mathbf{pq}}$. This step is straightforward. For simple bifurcations (as considered in this paper), the necessary calculations are easily done by hand, whereas more complex problems of higher codimension is a simple task for software tools such as Mathematica and Maple [24, 25].

The coefficients $\mathbf{g}_{\mathbf{pq}}$ (for the amplitude equation) and $\mathbf{h}_{\mathbf{pq}}$ (for the amplitude transformation) are now obtained order by order in an iterative procedure. At any order $(\mathbf{p}, \mathbf{q})$, any non-vanishing component $\mathbf{u}_i^* \cdot \mathbf{g}_{\mathbf{pq}}$ in the amplitude equation is given explicitly by

$$\mathbf{u}_i^* \cdot \mathbf{g}_{\mathbf{pq}} = \mathbf{u}_i^* \cdot \mathbf{\Phi}_{\mathbf{pq}}. \tag{135}$$

This term only appears if the resonance condition is fulfilled. To obtain the coefficient $\mathbf{h}_{\mathbf{pq}}$, one has to solve the system of linear equations

$$\Big(\mathbf{J} - \sum_{j=1}^{r} p_j \lambda_j \mathbf{I}\Big) \cdot \mathbf{h}_{\mathbf{pq}} = -\mathbf{Q}_{\mathbf{p}} \cdot \mathbf{\Phi}_{\mathbf{pq}} \qquad \text{(for flows)}, \tag{136a}$$

$$\Big(\mathbf{J} - \prod_{j=1}^{r} \lambda_j^{p_j} \mathbf{I}\Big) \cdot \mathbf{h}_{\mathbf{pq}} = -\mathbf{Q}_{\mathbf{p}} \cdot \mathbf{\Phi}_{\mathbf{pq}} \qquad \text{(for maps)} \tag{136b}$$

determining the non-resonant components of $\mathbf{h}_{\mathbf{pq}}$, with the auxiliary condition

$$\mathbf{R}_{\mathbf{p}} \cdot \mathbf{h}_{\mathbf{pq}} = \mathbf{0}, \tag{137}$$

which ensures that the resonant components of $\mathbf{h}_{\mathbf{pq}}$ vanish. Equation (136a) or (136b) together with (137) determine $\mathbf{h}_{\mathbf{pq}}$ completely.

This is all that is needed to formulate a given physical problem in terms of an amplitude equation. Notice carefully that the above procedure does *not* require that the Jacobian matrix has been transformed to block form — a feature that greatly simplifies the computations. The only non-trivial parts of the computations are the determination of the right and left eigenvectors associated with the bifurcating eigenvalues and the solution of the systems of linear equations (136).

Another significant result of the present paper is the compilation of general results for several types of bifurcations as summarized in Tables 1–4. This part of the work serves two important purposes. First we use it to demonstrate how the general procedure (sketched above) works in practice for flows and iterated maps. Secondly, it provides explicit expressions that can be used immediately for any specific problem. Such actual use of the tables is illustrated in Appendix A where the calculation of amplitude equations and associated transformations is demonstrated for a few specific problems, using the formulas of the tables.

As can be seen from the specific bifurcations discussed in Section 5 and the examples of the Appendix, the machinery is quite easy to use despite the array of expansions involved. In practice, these expansions are finite or can be truncated so that only few terms need be considered. Usually, only a few critical modes are involved. Thus the amplitude equation has few components, and in general one needs only include its first few terms to get a satisfactory description of the dynamics. The associated amplitude transformation can usually be truncated after the highest order included in the amplitude equation. We also emphasize that considerable simplification occurs in many applications as a result of the form of the vector field or map. For example, this is the case in chemical kinetics based on elementary reactions, which are at most of the second order. Consequently, the Taylor expansion (57) terminates at low order because higher order derivatives vanish. As mentioned previously, if the derivations by hand become too laborious, one can always carry it through by resorting to software package like Mathematica or Maple which are capable of performing symbolic computations

The main application of the results of the present paper is for determining the time evolution of dynamical systems near a local bifurcation. However, the derivation of an amplitude equation also provides an explicit expression for the center manifold in the simplest possible way.

In addition, the formulas of Tables 1–4 provide a general tool for determining numerical estimates of branchings of stationary, fixed points, and periodic solutions of flows and maps when a bifurcation is traversed. Such estimates are typically needed in continuation problems as implemented in the numerical software packages CONT [26, 27, pp. 302–361] and AUTO [28]. Estimates based on the solutions of amplitude equations are more accurate than those traditionally used in terms of tangents of the intersecting branches at the bifurcation point [29]. These do not include the curvature of the branches at the bifurcation and equally important — they do not determine the stability character (as super- or subcritical) of the bifurcation point. All of these issues are generally important when calculating delicate solution and bifurcation diagrams. For details regarding the numerical location of bifurcation points of the type discussed in this paper, we refer to [29–31] and references therein.

Notice also that the method presented here is generally valid also for stable and unstable manifolds. Except for accidental resonance, the differential equation describing the dynamics on these manifolds can in general be linearized to any order implying that all terms are non-resonant and therefore contained in the associated transformation.

As already mentioned in Sections 2 and 4, we emphasize that the theory for amplitude equations can be used directly to perform reductions of flows and iterated maps to normal form. Traditional approaches, where the normal form theorem is applied directly to a given problem, involves the determination of Lie brackets and solutions of the associated homological equation. As noted by Arrowsmith & Place [17], such calculations are often complicated and rather lengthy. The approach considered here, however, determines the normal form and the associated (normal form) transformation simply by solving systems of linear equations. From practical experience, we find the approach considered here much more convenient compared to traditional normal form reductions.

In this paper, we have worked out explicit formulas for a number of simple bifurcations. The derivation of these serve as an illustration of the general method presented but also provides a collection of results than can be useful for applications to specific systems: it may indeed save much time.

However, the method of deriving amplitude equations and associated transformations is absolutely straightforward also for more complicated local bifurcations (of codimension-two and higher). We have derived explicit amplitude equations and transformations for some of these higher bifurcations for flows and maps with the method described here. In this connection, it is natural to treat also bifurcations where the geometric multiplicity of the critical eigenvalues is smaller than the algebraic multiplicity. Such bifurcations can be treated in terms of generalized eigenvectors by straightforward modification of the present method. However, the general case requires a complicated notation, so we have not made the extension to generalized center eigenspace in the present paper. At the time of writing, we have worked out explicit expressions for coefficients of amplitude equations and transformations for a Bautin bifurcation (where a Hopf bifurcation changes from super- to subcritical and a quintic term is needed), for a Bogdanov-Takens bifurcation, for a fold-Hopf bifurcation, and for a "Hopf-Hopf" bifurcation (where two pairs of complex conjugate eigenvalues pass the imaginary axis) with and without strong resonances. For iterated maps, we have worked out the four cases of strong resonance for the Neimark-Sacker bifurcation.

In a future paper, we shall show how an amplitude equation for a fold-Hopf bifurcation can be applied on a quantitative level to describe a realistic reaction-diffusion model system for the Belousov-Zhabotinsky reaction under circumstances where the complex Ginzburg-Landau equation fails entirely. In fact, this observation suggests that such codimension-two descriptions may be much more useful than the codimension initially suggests. In particular, that paper will illustrate how results for amplitude equations and their associated transformations can be used to obtain a description in physical terms that may be compared quantitatively with the full model system and experimental data.

A Examples

In order to illustrate the theory discussed in the previous sections and demonstrate the use of the formulas of Tables 1–4, we discuss three simple examples. They will show the fundamental steps involved in calculating the amplitude equation for various bifurcations in actual systems. We emphasize that the use of amplitude equations for the particular examples discussed here has been chosen to illustrate the principles of the method for some simple bifurcations — not because it necessarily provides the computationally shortest path to the solution.

A.1 The Lorenz equations

To illustrate the derivation of amplitude equations for bifurcations involving a single zero eigenvalue, we consider the Lorenz equations [32]

$$\begin{pmatrix} \dot{x}_1 \\ \dot{x}_2 \\ \dot{x}_3 \end{pmatrix} = \begin{pmatrix} s(x_2 - x_1) \\ rx_1 - x_2 - x_1x_3 \\ -bx_3 + x_1x_2 \end{pmatrix}, \tag{138}$$

and choose the term r as the bifurcation parameter. One easily sees that (138) admits the trivial solution $(0,0,0)^{\mathrm{T}}$ with the corresponding Jacobian

$$\mathbf{J}(r) = \begin{pmatrix} -s & s & 0 \\ r & -1 & 0 \\ 0 & 0 & -b \end{pmatrix}, \tag{139}$$

which has a single real eigenvalue $\lambda = 0$ for $r = 1$. This implies that the Lorenz system has a one-dimensional center manifold at the stationary point $(0,0,0)^{\mathrm{T}}$ for $r = 1$. The right and left eigenvectors $\mathbf{u}$ and $\mathbf{u}^*$ of $\mathbf{J} = \mathbf{J}(1)$ are

$$\mathbf{u} = (1,1,0)^{\mathrm{T}}, \tag{140}$$

$$\mathbf{u}^* = \frac{1}{1+s}(1,s,0). \tag{141}$$

Second and third order terms

Since the coefficient σ_0 in Table 1 satisfies $\sigma_0 = \mathbf{u}^* \cdot \mathbf{F}_r = \mathbf{u}^* \cdot \frac{\partial \mathbf{F}}{\partial r}\Big|_{r=1} = 0$, we may exclude the possibility of a saddle-node bifurcation. Furthermore, since

$$\mathbf{F}_{\mathbf{xx}}(\boldsymbol{\xi}, \boldsymbol{\eta}) = (0, -\xi_1\eta_3 - \eta_1\xi_3, \xi_1\eta_2 + \eta_1\xi_1)^{\mathrm{T}}, \tag{142}$$

we may calculate the quadratic coefficient g_2 from Table 1 as

$$g_2 = \tfrac{1}{2}\mathbf{u}^* \cdot \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{u}) = \mathbf{u}^* \cdot (0,0,1)^{\mathrm{T}} = 0, \tag{143}$$

which excludes the possibility of a transcritical bifurcation. In order to determine the third order coefficient g_3, we must first find the coefficient vector $\mathbf{h}_{20}$. From Table 1 we get

$$\mathbf{J} \cdot \mathbf{h}_{20} = -(0,0,1)^{\mathrm{T}}, \tag{144}$$

$$\mathbf{u}^* \cdot \mathbf{h}_{20} = 0, \tag{145}$$

implying that $\mathbf{h}_{20} = (0,0,\frac{1}{b})^{\mathrm{T}}$. Observing that the Taylor expansion of (138) terminates at second order ($\mathbf{F}_{\mathbf{xxx}} = \mathbf{0}$), we may determine the cubic coefficient g_3 from Table 1 as

$$g_3 = \mathbf{u}^* \cdot \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{20}) = \mathbf{u}^* \cdot (0, -\frac{1}{b}, 0)^{\mathrm{T}} = -\frac{s}{b(1+s)}. \tag{146}$$

Unfolding terms
To find the coefficient σ_1 in the unfolding of the amplitude equation associated with pitchfork bifurcation (see Table 1), we first observe that $\mathbf{F}_r = \mathbf{0}$ implying that the coefficient vector $\mathbf{h}_{01}$ vanishes implying that the term $\mathbf{u}^* \cdot \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{01})$ in σ_1 disappears. Consequently, we get from Table 1

$$\sigma_1 = \mathbf{u}^* \cdot \mathbf{F}_{\mathbf{x}r} \cdot \mathbf{u} = \mathbf{u}^* \cdot \begin{pmatrix} 0 & 0 & 0 \\ 1 & 0 & 0 \\ 0 & 0 & 0 \end{pmatrix} \cdot \mathbf{u} = \frac{s}{s+1}. \tag{147}$$

For $s \neq 0$, we have $g_3 \neq 0$, and $\sigma_1 \neq 0$, and therefore conclude that a pitchfork bifurcation occurs in the Lorenz system (138) at $r = 1$. If $s > 0$ and $b > 0$, the bifurcation will be supercritical.

From Table 1, we now obtain the following expression for the amplitude equation for the Lorenz system (138)

$$\dot{z} = \frac{s}{s+1}\Big[(r-1)z - \frac{1}{b}z^3\Big], \tag{148}$$

which admits the non-trivial stationary solutions

$$z_{\pm} = \pm\sqrt{b(r-1)}. \tag{149}$$

To determine the branching behavior of (138) in the physical (x_1, x_2, x_3)-space, we use the amplitude transformation associated with the pitchfork bifurcation from Table 4. We find

$$\begin{pmatrix} x_1 \\ x_2 \\ x_3 \end{pmatrix}_{\pm} = \pm \begin{pmatrix} 1 \\ 1 \\ 0 \end{pmatrix} \sqrt{b(r-1)} + \begin{pmatrix} 0 \\ 0 \\ 1 \end{pmatrix} (r-1). \tag{150}$$

We have not shown the calculation of the coefficient vectors $\mathbf{h}_{30}$ and $\mathbf{h}_{11}$, since these accidentally cancel when inserted into the amplitude transformation.

A.2 The Gray-Scott model

As an example of a two-dimensional chemical system that exhibits a Hopf bifurcation, we consider the Gray-Scott model [33] for the transformation of a reactant A to a product B with two intermediate species X_1 and X_2:

$$\begin{aligned} \mathrm{A} &\xrightarrow{k_1} \mathrm{X_1} \\ \mathrm{X_1} + 2\mathrm{X_2} &\xrightarrow{k_2} 3\mathrm{X_2} \\ \mathrm{X_2} &\xrightarrow{k_3} \mathrm{B} \end{aligned}$$

Introducing dimensionless concentrations by $x_1 = \sqrt{k_2/k_1}[\mathrm{X_1}]$ and $x_2 = \sqrt{k_2/k_1}[\mathrm{X_2}]$, a dimensionless time by $\tau = k_1 t$, and choosing $k_3 = k_1$ the scaled kinetic equations become

$$\begin{pmatrix} \dot{x}_1 \\ \dot{x}_2 \end{pmatrix} = \begin{pmatrix} \nu - x_1 x_2^2 \\ x_1 x_2^2 - x_2 \end{pmatrix}, \tag{151}$$

where $\nu = \sqrt{k_2/k_1}[\mathrm{A}]$ is used as bifurcation parameter. Here we consider the stationary solution $\mathbf{x_s} = (\frac{1}{\nu}, \nu)$. The Jacobian of (151) at $\mathbf{x}_s$ is

$$\mathbf{J}(\nu) = \begin{pmatrix} -\nu^2 & -2 \\ \nu^2 & 1 \end{pmatrix} \tag{152}$$

For $\nu = 1$ the Jacobian $\mathbf{J}$ has eigenvalues $\lambda_1 = \overline{\lambda}_2 = \mathrm{i}$ implying that the system exhibits a Hopf bifurcation. The first order terms are given by the right and left complex eigenvectors $\mathbf{u}$ and $\mathbf{u}^*$ associated with λ_1. We get

$$\mathbf{u} = (-2, 1+\mathrm{i})^{\mathrm{T}} \qquad \text{and} \qquad \mathbf{u}^* = -\frac{1}{4}(1+\mathrm{i}, 2\,\mathrm{i})^{\mathrm{T}}. \tag{153}$$

The second and third order terms can be obtained from Table 2 by calculating $\mathbf{F_{xx}}$ and $\mathbf{F_{xxx}}$ at the bifurcation point where $\nu = 1$ and $\mathbf{x_s} = (1, 1)^{\mathrm{T}}$. By definition

$$\mathbf{F_{xx}}(\boldsymbol{\xi}, \boldsymbol{\eta}) = \sum_{i,j=1}^{2} \left.\frac{\partial^2 \mathbf{F}}{\partial x_i \partial x_j}\right|_{\mathbf{x}_\mathrm{s}} \xi_i \eta_j \qquad \text{and} \qquad \mathbf{F_{xxx}}(\boldsymbol{\xi}, \boldsymbol{\eta}, \boldsymbol{\zeta}) = \sum_{i,j,k=1}^{2} \left.\frac{\partial^3 \mathbf{F}}{\partial x_i \partial x_j \partial x_k}\right|_{\mathbf{x}_\mathrm{s}} \xi_i \eta_j \zeta_k. \tag{154}$$

From (151) and (154), we get

$$\left.\frac{\partial^2 \mathbf{F}}{\partial x_1^2}\right|_{\mathbf{x}_\mathrm{s}} = \begin{pmatrix} 0 \\ 0 \end{pmatrix}, \qquad \left.\frac{\partial^2 \mathbf{F}}{\partial x_1 \partial x_2}\right|_{\mathbf{x}_\mathrm{s}} = \left.\frac{\partial^2 \mathbf{F}}{\partial x_2 \partial x_1}\right|_{\mathbf{x}_\mathrm{s}} = \left.\frac{\partial^2 \mathbf{F}}{\partial x_2^2}\right|_{\mathbf{x}_\mathrm{s}} = \begin{pmatrix} -2 \\ 2 \end{pmatrix}. \tag{155}$$

Second order terms
From (154) and (155) we get

$$\boldsymbol{\Phi}_{200} = \tfrac{1}{2}\mathbf{F_{xx}}(\mathbf{u}, \mathbf{u}) = (8 + 2\,\mathrm{i}, -8 - 2\,\mathrm{i})^{\mathrm{T}}, \tag{156}$$

$$\boldsymbol{\Phi}_{110} = \mathbf{F_{xx}}(\mathbf{u}, \overline{\mathbf{u}}) = (4, -4)^{\mathrm{T}}. \tag{157}$$

The coefficients $\mathbf{h}_{200}$, $\mathbf{h}_{020}$, and $\mathbf{h}_{110}$ can then be found by solving the linear equations

$$(\mathbf{J} - 2\,\mathrm{i}\,\mathbf{I})\cdot\mathbf{h}_{200} = -\boldsymbol{\Phi}_{200} = -(4 + 2\,\mathrm{i}, -4 - 2\,\mathrm{i})^{\mathrm{T}}, \tag{158}$$

$$\mathbf{J}\cdot\mathbf{h}_{110} = -\boldsymbol{\Phi}_{110} = -(4, -4)^{\mathrm{T}}. \tag{159}$$

giving

$$\mathbf{h}_{200} = \overline{\mathbf{h}}_{020} = -\frac{2}{3}(5\,\mathrm{i}, 2 - 4\,\mathrm{i})^{\mathrm{T}}, \tag{160}$$

$$\mathbf{h}_{110} = (4, 0)^{\mathrm{T}}. \tag{161}$$

Third order terms
From (151), (154),(160), and (161), we get

$$\mathbf{F_{xx}}(\mathbf{u}, \mathbf{h}_{200}) = -\frac{4}{3}(3 - 11\,\mathrm{i})\mathbf{v}, \qquad \mathbf{F_{xx}}(\mathbf{u}, \mathbf{h}_{110}) = -(2 + 6\,\mathrm{i})\mathbf{v}, \qquad \mathbf{F_{xx}}(\overline{\mathbf{u}}, \mathbf{h}_{200}) = -\frac{4}{3}(1 - 7\,\mathrm{i})\mathbf{v},$$
$$\mathbf{F_{xxx}}(\mathbf{u}, \mathbf{u}, \mathbf{u}) = 24\,\mathrm{i}\,\mathbf{v}, \qquad \mathbf{F_{xxx}}(\mathbf{u}, \mathbf{u}, \overline{\mathbf{u}}) = (16 + 8\,\mathrm{i})\mathbf{v}, \tag{162}$$

where $\mathbf{v} = (1, -1)^{\mathrm{T}}$. The third order coefficients can then be found by solving the following linear equations. Solving

$$(\mathbf{J} - 3\,\mathrm{i}\,\mathbf{I})\cdot\mathbf{h}_{300} = -\boldsymbol{\Phi}_{300} = -\frac{4}{3}(3 - 14\,\mathrm{i}, -3 + 14\,\mathrm{i})^{\mathrm{T}} \tag{163}$$

gives

$$\mathbf{h}_{300} = \overline{\mathbf{h}}_{030} = -\frac{1}{6}(-45 + 5\,\mathrm{i}, 42 + 9\,\mathrm{i})^{\mathrm{T}}. \tag{164}$$

Solving

$$\begin{aligned}(\mathbf{J}-\mathrm{i}\,\mathbf{I})\cdot\mathbf{h}_{210} &= -\boldsymbol{\Phi}_{210} = -\frac{4}{3}(1-4\,\mathrm{i},-1+4\,\mathrm{i})^{\mathrm{T}},\\ \mathbf{u}^{*}\cdot\mathbf{h}_{210} &= 0,\end{aligned} \tag{165}$$

gives

$$\mathbf{h}_{210} = \overline{\mathbf{h}}_{120} = \frac{1}{3}(3+5\,\mathrm{i},-4-\mathrm{i}). \tag{166}$$

Using Table 2, we may find the resonant coefficient g_3 from (163) as

$$g_3 = \mathbf{u}^{*}\cdot\boldsymbol{\Phi}_{210} = -(1+\frac{5}{3}\,\mathrm{i}). \tag{167}$$

Here we notice that the resonant coefficient satisfies $\mathrm{Re}\,g_3 < 0$ for all ν showing that the Hopf bifurcation is always supercritical.

Unfolding terms

We first note that

$$\mathbf{F}_{\nu} = \left.\frac{\partial\mathbf{F}}{\partial\nu}\right|_{\mathbf{x}_{\mathrm{s}}} = (1,0)^{\mathrm{T}}, \tag{168}$$

implying that $\mathbf{h}_{001}$ can be found from the equation

$$\mathbf{J}\cdot\mathbf{h}_{001} = -(1,0)^{\mathrm{T}}, \tag{169}$$

giving

$$\mathbf{h}_{001} = (-1,1)^{\mathrm{T}}. \tag{170}$$

Observing that $\mathbf{F}_{\mathbf{x}\nu} = \mathbf{0}$, we may calculate the coefficient σ_1 as

$$\sigma_1 = \mathbf{u}^{*}\cdot\mathbf{F}_{\mathbf{x}\mathbf{x}}(\mathbf{u},\mathbf{h}_{001}) = -1+\mathrm{i}\,. \tag{171}$$

Finally, we may find the coefficient vector $\mathbf{h}_{101}$ by solving

$$\begin{aligned}(\mathbf{J}-\mathrm{i}\,\mathbf{I})\cdot\mathbf{h}_{101} &= (4,-4)^{\mathrm{T}},\\ \mathbf{u}^{*}\cdot\mathbf{h}_{101} &= 0,\end{aligned} \tag{172}$$

which gives

$$\mathbf{h}_{101} = \overline{\mathbf{h}}_{011} = (1-\mathrm{i},\mathrm{i})^{\mathrm{T}}. \tag{173}$$

Amplitude equation

In conclusion, the amplitude equation (100) associated with the supercritical Hopf bifurcation in the Gray-Scott model becomes

$$\dot{z} = \mathrm{i}\,z - (1-\mathrm{i})\nu z - (1+\frac{5}{3}\,\mathrm{i})z|z|^2. \tag{174}$$

Any solution to the amplitude equation can then be transformed back to the concentration space by using

$$\begin{aligned}\mathbf{x} = \begin{pmatrix}1\\1\end{pmatrix} + \begin{pmatrix}-1\\1\end{pmatrix}\nu + \left[\begin{pmatrix}-2\\1+\mathrm{i}\end{pmatrix}z + \text{c.c.}\right] - \frac{2}{3}\left[\begin{pmatrix}5\,\mathrm{i}\\2-4\,\mathrm{i}\end{pmatrix}z^2 + \text{c.c.}\right] - \begin{pmatrix}4\\0\end{pmatrix}|z|^2 - \\ \frac{1}{6}\left[\begin{pmatrix}-45+5\,\mathrm{i}\\42+9\,\mathrm{i}\end{pmatrix}z^3 + 2\begin{pmatrix}3+5\,\mathrm{i}\\-4-\mathrm{i}\end{pmatrix}z|z|^2 + \text{c.c.}\right] + \left[\begin{pmatrix}1+\mathrm{i}\\\mathrm{i}\end{pmatrix}\nu z + \text{c.c.}\right],\end{aligned} \tag{175}$$

where c.c. denotes the complex conjugate of all terms within a particular square bracket.

A.3 The Hénon map

As an example of an iterated map which exhibits a period doubling bifurcation, we consider the Hénon map [34]

$$\begin{pmatrix} x_1 \\ x_2 \end{pmatrix} \mapsto \begin{pmatrix} a - x_1^2 + bx_2 \\ x_1 \end{pmatrix}, \tag{176}$$

and derive an explicit amplitude equation for it using the parameter a as bifurcation parameter. We observe that (176) admits the non-trivial fixed point solution

$$x_1 = x_2 = \frac{1}{2}(b - 1 + \sqrt{4a - (b-1)^2}\,), \tag{177}$$

with corresponding Jacobian

$$\mathbf{J}(a) = \begin{pmatrix} 1 - b - \sqrt{4a + (b-1)^2)} & b \\ 1 & 0 \end{pmatrix}. \tag{178}$$

Clearly, $\mathbf{J}(a)$ has an eigenvalue $\lambda = -1$ if

$$a = \frac{3(b-1)^2}{4}. \tag{179}$$

The right and left eigenvectors associated with the critical eigenvalue are

$$\mathbf{u} = (-1, 1)^{\mathrm{T}}, \tag{180}$$

$$\mathbf{u}^* = \frac{1}{1+b}(-1, b). \tag{181}$$

Second and third order terms
Observing that $\mathbf{F_{xx}}(\boldsymbol{\xi}, \boldsymbol{\eta}) = (-2\xi_1\eta_1, 0)^{\mathrm{T}}$, we find

$$\tfrac{1}{2}\mathbf{F_{xx}}(\mathbf{u}, \mathbf{u}) = (-1, 0)^{\mathrm{T}}. \tag{182}$$

The second order coefficient vector $\mathbf{h}_{20}$ can then be found from Table 3 by solving the linear equation

$$(\mathbf{J} - \mathbf{I})\cdot\mathbf{h}_{20} = (1, 0)^{\mathrm{T}}, \tag{183}$$

namely

$$\mathbf{h}_{20} = \frac{1}{2(b-1)}(1, 1)^{\mathrm{T}}. \tag{184}$$

Noting that $\mathbf{F_{xxx}} = \mathbf{0}$, we use Table 3 and calculate the third order resonant term g_3 as

$$g_3 = \mathbf{u}^*\cdot\mathbf{F_{xx}}(\mathbf{u}, \mathbf{h}_{20}) = \mathbf{u}^*\cdot(\frac{1}{b-1}, 0)^{\mathrm{T}} = \frac{1}{1-b^2}. \tag{185}$$

Unfolding terms
To find the unfolding of the amplitude equation associated with the period doubling in (176), we first determine the constant coefficient vector $\mathbf{h}_{01}$. From Table 3, we get

$$(\mathbf{J} - \mathbf{I})\cdot\mathbf{h}_{01} = -\mathbf{F}_a = -(1, 0)^{\mathrm{T}} \tag{186}$$

which readily is solved for $\mathbf{h}_{01}$ as

$$\mathbf{h}_{01} = \frac{1}{2(1-b)}(1,1)^{\mathrm{T}}. \tag{187}$$

Here we note that all elements of the matrix $\mathbf{F}_{\mathbf{x}a}$ are zero. Using Table 3, we conclude that the unfolding coefficient σ_1 becomes

$$\sigma_1 = \mathbf{u}^* \cdot \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{01}) = \frac{1}{b^2-1}. \tag{188}$$

If we furthermore define the distance μ from the bifurcation point as $\mu = a - \frac{3(1-b)^2}{4}$, we arrive at the following amplitude equation for the period doubling bifurcation in the Hénon map (176)

$$z \mapsto (\frac{1}{b^2-1}\mu - 1)z + \frac{1}{1-b^2}z^3. \tag{189}$$

For the doubly iterate of the amplitude equation, we find the following two non-trivial fixed point solutions

$$z_\pm = \pm\sqrt{\mu}. \tag{190}$$

For the Hénon map, this corresponds to the emergence of a two stable period-two orbits whose location in (x_1, x_2)-phase space and parametric dependence on μ is determined via the amplitude transformation from Table 4 as

$$\begin{pmatrix} x_1 \\ x_2 \end{pmatrix}_\pm = \tfrac{1}{2}(1-b)\begin{pmatrix} 1 \\ 1 \end{pmatrix}\sqrt{\mu} \pm \begin{pmatrix} -1 \\ 1 \end{pmatrix}\sqrt{\mu} + \frac{1}{2(b-1)}\begin{pmatrix} 1 \\ 1 \end{pmatrix}\mu. \tag{191}$$

Just as in the Lorenz model (138), we have not shown the calculation of the coefficient vectors $\mathbf{h}_{30}$ and $\mathbf{h}_{11}$, since these accidentally cancel when inserted into the amplitude transformation.

References

[1] M. Ipsen, Ph.D. thesis, University of Copenhagen, Department of Chemistry, 1997.

[2] M. Ipsen, F. Hynne, and P. G. Sørensen, Int. J. Bifurcation and Chaos **7**, 1539 (97).

[3] A. C. Newell, Lectures in Appl. Math **15**, 157 (1974).

[4] Y. Kuramoto, *Chemical Oscillations Waves and Turbulence* (Springer-Verlag, Berlin, 1984).

[5] A. C. Newell and J. V. Moloney, *Non-linear Optics* (Addison-Wesley, California, 1992).

[6] G. Nicolis, *Introduction to Nonlinear Science* (Cambridge University Press, Cambridge, 1995).

[7] D. Bruno, *Local Methods in Nonlinear Differential Equations*, *Springer Series in Soviet Mathematics* (Springer Verlag, New York, 1989).

[8] Y. A. Kuznetsov, *Elements of Applied Bifurcation Theory* (Springer-Verlag, New York, 1995).

[9] J. Guckenheimer and P. J. Holmes, *Nonlinear Oscillations, Dynamical Systems and Bifurcations of Vector Fields* (Springer-Verlag, New York, 1983).

[10] P. H. Coullet and E. A. Spiegel, SIAM J. Appl. Math. **43**, 776 (1983).

[11] C. Elphick *et al.*, Physica D **29**, 95 (1987).

[12] Golubitsky, I. Stewart, and P. G. Schaeffer, *Singularities and Groups in Bifurcation Theory* (Springer-Verlag, New York, 1988), Vol. 2.

[13] J. D. Crawford, Rev. Mod. Phys **63**, 991 (1991).

[14] G. Iooss and D. D. Joseph, *Elementary Stability and Bifurcation Theory*, 2 ed. (Springer-Verlag, New York, 1980,1990).

[15] B. D. Hassard, N. D. Kazarinoff, and Y.-H. Wan, *Theory and Applications of Hopf Bifurcation*, No. 41 in *London Mathematical Society Lecture Note Series* (Cambridge University Press, Cambridge, 1981).

[16] V. I. Arnold, *Geometrical Methods in the Theory of Ordinary Differential Equations* (Springer-Verlag, New York, 1983).

[17] D. K. Arrowsmith and C. M. Place, *An Introduction to Dynamical Systems* (Cambridge University Press, Cambridge, 1990).

[18] G. H. Golub and C. F. V. Loan, *Matrix Computations*, 3 ed. (The Johns Hopkins University Press, Baltimore, 1996).

[19] L. D. Landau, C. R. Dokl. Acad. Sci. URSS **44**, 311 (1944).

[20] J. T. Stuart, J. Fluid Mech **9**, 353 (1960).

[21] T. Kato, *Perturbation Theory for Linear Operators* (Springer-Verlag, Berlin, 1966).

[22] F. Hynne, P. G. Sørensen, and K. Nielsen, J. Chem. Phys **92**, 1747 (1990).

[23] F. Hynne and P. G. Sørensen, Phys. Rev. E **48**, 4106 (1993).

[24] S. Wolfram, *The Mathematica Book*, 3 ed. (Cambridge University Press, Cambridge, UK, 1996).

[25] M. B. Monagan *et al.*, *Maple V Programming Guide* (Springer-Verlag, New York, 1996).

[26] I. Schreiber, *CONT — A Program for Construction of Parameter Dependence of Stationary or Periodic Solutions of Ordinary Differential or Difference Equations*, Department of Chemical Engineering, Prague Institute of Chemical Technology, 1995.

[27] M. Marek and I. Schreiber, *Chaotic Behavior of Deterministic Dissipative Systems* (Academia, Prague, 1991).

[28] E. J. Doedel *et al.*, *AUTO 97: Continuation and Bifurcation Software for Ordinary Differential Equations (with HomCont)*, 1997.

[29] M. Kubíček and M. Marek, *Computational Methods in Bifurcation Theory and Dissipative Structures* (Springer-Verlag, New York, 1983).

[30] M. Holodniok and M. Kubíček, Math. Comp. Sim **29**, 33 (1987).

[31] W.-J. Beyn, in *Nonlinear Partial Differential Equations and Dynamical Systems*, Vol. 1 of *Advances in Numerical Analysis*, edited by W. Light (Clarendon Press, Oxford, 1991), Chap. 5, pp. 175–236.

[32] E. N. Lorenz, J. Atmos. Sci **20**, 130 (1963).

[33] P. Gray and S. K. Scott, J. Phys. Chem **89**, 22 (1985).

[34] M. Hénon, Comm. Math. Phys **50**, 69 (1976).

Captions of tables and figures

Figure 1: Geometrical illustration of the parameterization of the center manifold by (3). A point $\mathbf{z} \in E^{\mathrm{c}}$ is mapped by the transformation $\mathbf{h}$ to the point $\mathbf{h}(\mathbf{z})$ so that $\mathbf{z} + \mathbf{h}(\mathbf{z}) \in W^{\mathrm{c}}$.

Table 1: Expressions for calculating the coefficients of the amplitude transformation and the amplitude equation for each of six bifurcations: saddle-node, transcritical, and pitchfork bifurcations for flows and iterated maps. At the bifurcation, the Jacobian $\mathbf{J}$ has right and left eigenvectors $\mathbf{u}$ and $\mathbf{u}^*$ respectively corresponding to a critical eigenvalue $\lambda = 0$ for flows and $\lambda = 1$ for iterated maps. The amplitude transformation $\mathbf{x} = \mathbf{z} + \mathbf{h}(\mathbf{z}, \mu)$, $\mathbf{z} = \mathbf{u}z$, transforms a solution $z(t)$ of the amplitude equation to the motion $\mathbf{x}(t)$ on the unfolded center manifold for the dynamical system. The vector coefficients $\mathbf{h}_{pq}$ written as $\mathbf{h}_p$) are determined as solutions to the linear equations indicated, in terms of the derivatives of the vector field $\mathbf{F}$. The coefficients of the amplitude equations can then be found through the explicit expressions indicated, in terms of $\mathbf{F}$ and $\mathbf{h}_{pq}$.

Table 2: Formulae for calculating the coefficients of the amplitude transformation and the amplitude equation for the Hopf bifurcation and the Neimark-Sacker bifurcation. At the bifurcation, the Jacobian $\mathbf{J}$ has two complex conjugate eigenvectors $\mathbf{u}$ and $\overline{\mathbf{u}}$ and left eigenvectors $\mathbf{u}^*$ and $\overline{\mathbf{u}}^*$ corresponding to critical eigenvalues $\lambda = \pm\,\mathrm{i}\,\omega_0$ for flows (Hopf bifurcation) and $\lambda = \mathrm{e}^{\pm\,\mathrm{i}\theta_0}$ for iterated maps (Neimark-Sacker bifurcation). The amplitude transformation $\mathbf{x} = \mathbf{z} + \mathbf{h}(\mathbf{z}, \mu)$, $\mathbf{z} = \mathbf{u}z + \overline{\mathbf{u}}\overline{z}$, transforms a solution $z(t)$ of the amplitude equation to the motion $\mathbf{x}(t)$ on the unfolded center manifold for the dynamical system. The vector coefficients $\mathbf{h}_{ijk}$ are determined as solutions to the linear equations indicated, in terms of the derivatives of the vector field $\mathbf{F}$. The coefficients of the amplitude equations can then be found through the explicit expressions indicated, in terms of $\mathbf{F}$ and $\mathbf{h}_{ijk}$.

Table 3: Expressions for calculating the coefficients of the amplitude transformation and the amplitude equation for the period doubling bifurcation. At the bifurcation, the Jacobian $\mathbf{J}$ has right and left eigenvectors $\mathbf{u}$ and $\mathbf{u}^*$ respectively corresponding to a critical eigenvalue $\lambda = -1$. The amplitude transformation $\mathbf{z} + \mathbf{h}(\mathbf{z}, \mu)$, $\mathbf{z} = \mathbf{u}z$, transforms a solution $z(t)$ to the amplitude equation to the motion $\mathbf{x}(t)$ on the unfolded center manifold for the dynamical system. The vector coefficients $\mathbf{h}_{pq}$ are determined as solutions to the linear equations indicated, in terms of the derivatives of the vector field $\mathbf{F}$. The coefficients of the amplitude equation can then be found through the explicit expressions indicated, in terms of $\mathbf{F}$ and $\mathbf{h}_{pq}$.

Table 4: Table showing the limit set solutions (stationary points, fixed points, or period orbits) arising from: a) saddle-node, transcritical, and pitchfork bifurcations in flows and iterated maps, b) Hopf bifurcations in flows, and c) period doubling and Neimark-Sacker bifurcation in iterated maps. The second column shows the well-known solutions to the amplitude equation, whereas column three gives the physical representation of these in terms of the amplitude transformation. Since the period doubling in an iterated map corresponds to a pitchfork bifurcation in the doubly iterated map, the results for these two bifurcations are identical as indicated in the table. The solution shown for the Hopf and Neimark-Sacker bifurcation corresponds to a periodic solution for the Hopf bifurcation. The limit cycle corresponds to the invariant ellipse emerging at the Neimark-Sacker bifurcation.



Figure 1:

Bifurcation	*Saddle-node*	*Transcritical*	*Pitchfork*
Transformation $\mathbf{x} = \mathbf{z} + \mathbf{h}(\mathbf{z}, \mu)$	$\mathbf{x} = \mathbf{u}z + \mathbf{h}_{20}z^2 + \mathbf{h}_{01}\mu$	$\mathbf{x} = \mathbf{u}z + \mathbf{h}_{20}z^2 + \mathbf{h}_{01}\mu + \mathbf{h}_{11}z\mu$	$\mathbf{x} = \mathbf{u}z + \mathbf{h}_{20}z^2 + \mathbf{h}_{30}z^3 + \mathbf{h}_{01}\mu + \mathbf{h}_{11}z\mu$
Linear equations for $\mathbf{h}_{pq}$	z^2: $\mathbb{J}\cdot\mathbf{h}_{20} = -\frac{1}{2}\mathbf{Q}\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{u})$ $\mathbf{u}^*\cdot\mathbf{h}_{20} = 0$ μ: $\mathbb{J}\cdot\mathbf{h}_{01} = -\mathbf{Q}\cdot\mathbf{F}_{\mu}$ $\mathbf{u}^*\cdot\mathbf{h}_{01} = 0$	z^2: $\mathbb{J}\cdot\mathbf{h}_{20} = -\frac{1}{2}\mathbf{Q}\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{u})$ $\mathbf{u}^*\cdot\mathbf{h}_{20} = 0$ μ: $\mathbb{J}\cdot\mathbf{h}_{01} = -\mathbf{F}_{\mu}$ $\mathbf{u}^*\cdot\mathbf{h}_{01} = 0$ μz: $\mathbb{J}\cdot\mathbf{h}_{11} = -\mathbf{Q}\cdot\big(\mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{01})\big)$ $\mathbf{u}^*\cdot\mathbf{h}_{11} = 0$	z^2: $\mathbb{J}\cdot\mathbf{h}_{20} = -\frac{1}{2}\mathbf{Q}\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{u})$ $\mathbf{u}^*\cdot\mathbf{h}_{20} = 0$ z^3: $\mathbb{J}\cdot\mathbf{h}_{30} = -\mathbf{Q}\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{20}) + \frac{1}{6}\mathbf{Q}\cdot\mathbf{F}_{\mathbf{xxx}}(\mathbf{u},\mathbf{u},\mathbf{u})$ $\mathbf{u}^*\cdot\mathbf{h}_{30} = 0$ μ: $\mathbb{J}\cdot\mathbf{h}_{01} = -\mathbf{F}_{\mu}$ $\mathbf{u}^*\cdot\mathbf{h}_{01} = 0$ μz: $\mathbb{J}\cdot\mathbf{h}_{11} = -\mathbf{Q}\cdot\big(\mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{01})\big)$ $\mathbf{u}^*\cdot\mathbf{h}_{11} = 0$
Resonant coefficients	$g_2 = \frac{1}{2}\mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{u})$ $\sigma_0 = \mathbf{u}^*\cdot\mathbf{F}_{\mu}$	$g_2 = \frac{1}{2}\mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{u})$ $\sigma_1 = \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{01})$	$g_3 = \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{20}) + \frac{1}{6}\mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xxx}}(\mathbf{u},\mathbf{u},\mathbf{u})$ $\sigma_1 = \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{01})$
Amplitude equation	$\dot{z} = \sigma_0\mu + g_2z^2$ $z \mapsto \sigma_0\mu + z + g_2z^2$	$\dot{z} = \sigma_1\mu z + g_2z^2$ $z \mapsto (1+\sigma_1\mu)z + g_2z^2$	$\dot{z} = \sigma_1\mu z + g_3z^3$ $z \mapsto (1+\sigma_1\mu)z + g_3z^3$
$\mathbb{J} = \mathbf{J}$ for flows, $\mathbb{J} = \mathbf{J} - \mathbf{I}$ for iterated maps, $\mathbf{Q}\cdot\mathbf{x} = \mathbf{x} - (\mathbf{u}^*\cdot\mathbf{x})\mathbf{u}$.			

Table 1:

Hopf and Neimark-Sacker Bifurcations	
Transformation $\mathbf{x} = \mathbf{z} + \mathbf{h}(\mathbf{z},\mu)$	$\mathbf{x} = \mathbf{u}z + \overline{\mathbf{u}z} + \mathbf{h}_{200}z^2 + \mathbf{h}_{110}\lvert z\rvert^2 + \mathbf{h}_{020}\overline{z}^2 + \mathbf{h}_{300}z^3 + \mathbf{h}_{210}\lvert z\rvert^2 z +$ $\mathbf{h}_{120}\lvert z\rvert^2\overline{z} + \mathbf{h}_{030}\overline{z}^3 + \mathbf{h}_{001}\mu + (\mathbf{h}_{101}z + \mathbf{h}_{011}\overline{z})\mu$
Linear equations for $\mathbf{h}_{ijk}$	z^2: $(\mathbf{J}-\gamma_2\mathbf{I})\cdot\mathbf{h}_{200} = -\frac{1}{2}\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{u})$ $\mathbf{h}_{020} = \overline{\mathbf{h}}_{200}$ $\lvert z\rvert^2$: $(\mathbf{J}-\gamma_0\mathbf{I})\cdot\mathbf{h}_{110} = -\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\overline{\mathbf{u}})$ z^3: $(\mathbf{J}-\gamma_3\mathbf{I})\cdot\mathbf{h}_{300} = -\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{200}) - \frac{1}{6}\mathbf{F}_{\mathbf{xxx}}(\mathbf{u},\mathbf{u},\mathbf{u}),$ $\mathbf{h}_{030} = \overline{\mathbf{h}}_{300}$ $z\lvert z\rvert^2$: $(\mathbf{J}-\gamma_1\mathbf{I})\cdot\mathbf{h}_{210} = -\mathbf{Q}\cdot\big(\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{110}) + \mathbf{F}_{\mathbf{xx}}(\overline{\mathbf{u}},\mathbf{h}_{200}) + \frac{1}{2}\mathbf{F}_{\mathbf{xxx}}(\mathbf{u},\mathbf{u},\overline{\mathbf{u}})\big)$ $\mathbf{u}^*\cdot\mathbf{h}_{210} = 0$ $\mathbf{h}_{120} = \overline{\mathbf{h}}_{210}$ μ: $(\mathbf{J}-\gamma_0\mathbf{I})\cdot\mathbf{h}_{001} = -\mathbf{F}_\mu$ μz: $(\mathbf{J}-\gamma_1\mathbf{I})\cdot\mathbf{h}_{101} = -\mathbf{Q}\cdot\big(\mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{001})\big)$ $\mathbf{u}^*\cdot\mathbf{h}_{101} = 0$ $\mathbf{h}_{011} = \overline{\mathbf{h}}_{101}$
Resonant coefficients	$g_3 = \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{110}) + \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\overline{\mathbf{u}},\mathbf{h}_{200}) + \frac{1}{2}\mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xxx}}(\mathbf{u},\mathbf{u},\overline{\mathbf{u}})$ $\sigma_1 = \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u},\mathbf{h}_{001})$
Amplitude equation	$\dot{z} = (\mathrm{i}\,\omega_0 + \sigma_1\mu)z + g_3 z\lvert z\rvert^2$ $z \mapsto (\mathrm{e}^{\mathrm{i}\theta_0} + \sigma_1\mu)z + g_3 z\lvert z\rvert^2$
$\gamma_k = k\,\mathrm{i}\,\omega_0$ for flows, $\gamma_k = \mathrm{e}^{k\mathrm{i}\theta_0}$ for iterated maps, $\mathbf{Q}\cdot\mathbf{x} = \mathbf{x} - (\mathbf{u}^*\cdot\mathbf{x})\mathbf{u}$.	

Table 2:

Period Doubling Bifurcation	
Transformation $\mathbf{x} = \mathbf{z} + \mathbf{h}(\mathbf{z}, \mu)$	$\mathbf{x} = \mathbf{u}z + \mathbf{h}_{20}z^2 + \mathbf{h}_{30}z^3 + \mathbf{h}_{01}\mu + \mathbf{h}_{11}\mu z$
Linear equations for $\mathbf{h}_{pq}$	z^2: $(\mathbf{J} - \mathbf{I})\cdot\mathbf{h}_{20} = -\frac{1}{2}\mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{u})$ z^3: $(\mathbf{J} + \mathbf{I})\cdot\mathbf{h}_{30} = -\mathbf{Q}\cdot\big(\mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{20}) + \frac{1}{6}\mathbf{F}_{\mathbf{xxx}}(\mathbf{u}, \mathbf{u}, \mathbf{u})\big)$ $\mathbf{u}^*\cdot\mathbf{h}_{30} = 0$ μ: $(\mathbf{J} - \mathbf{I})\cdot\mathbf{h}_{01} = -\mathbf{F}_{\mu}$ μz: $(\mathbf{J} + \mathbf{I})\cdot\mathbf{h}_{11} = -\mathbf{Q}\cdot\big(\mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{01})\big)$ $\mathbf{u}^*\cdot\mathbf{h}_{11} = 0$
Resonant coefficients	$g_3 = \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{20}) + \frac{1}{6}\mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xxx}}(\mathbf{u}, \mathbf{u}, \mathbf{u})$ $\sigma_1 = \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{x}\mu}\cdot\mathbf{u} + \mathbf{u}^*\cdot\mathbf{F}_{\mathbf{xx}}(\mathbf{u}, \mathbf{h}_{01})$
Amplitude equation	$z \mapsto (\sigma_1\mu - 1)z + g_3z^3$
$\mathbf{Q}\cdot\mathbf{x} = \mathbf{x} - (\mathbf{u}^*\cdot\mathbf{x})\mathbf{u}$.	

Table 3:

	Limit set solutions		
Bifurcation	*Amplitude space*	*Physical space*	*Solution diagram*
Saddle-node	$z_\pm = \pm a, \quad a = \sqrt{-\frac{\sigma_0 \mu}{g_2}}$	$\mathbf{x}_\pm = \pm \mathbf{u} a + \mathbf{h}_{20} a^2 + \mathbf{h}_{01} \mu$	
Transcritical	$z_+ = a, \quad a = -\frac{\sigma_1 \mu}{g_2}$ $z_0 = 0$	$\mathbf{x}_+ = \mathbf{u} a + \mathbf{h}_{20} a^2 + \mathbf{h}_{01} \mu + \mathbf{h}_{11} a \mu$ $\mathbf{x}_0 = \mathbf{h}_{01} \mu$	
Pitchfork/ Period doubling	$z_\pm = \pm a, \quad a = \sqrt{-\frac{\sigma_1 \mu}{g_3}}$ $z_0 = 0$	$\mathbf{x}_\pm = \pm \mathbf{u} a + \mathbf{h}_{20} a^2 \pm \mathbf{h}_{30} a^3 + \mathbf{h}_{01} \mu \pm \mathbf{h}_{11} a \mu$ $\mathbf{x}_0 = \mathbf{h}_{01} \mu$	
Hopf/Neimark	$z = a e^{\mathrm{i}\,\omega t}, \quad z_0 = 0,$ $a = \sqrt{-\sigma_1' \mu / g_3'},$ $\omega = \omega_0 + (\sigma_1'' - \frac{g_3''}{g_3'} \sigma_1') \mu,$ $g_3 = g_3' + \mathrm{i}\, g_3'', \quad \sigma_1 = \sigma_1' + \mathrm{i}\, \sigma_1''$	$\mathbf{x} = \big[\mathbf{u} a e^{\mathrm{i}\,\omega t} + \mathbf{h}_{200} a^2 e^{2\,\mathrm{i}\,\omega t} + \mathbf{h}_{300} a^3 e^{3\,\mathrm{i}\,\omega t} +$ $\mathbf{h}_{210} a^3 e^{\mathrm{i}\,\omega t} + \mathbf{h}_{101} a e^{\mathrm{i}\,\omega t} \mu + \text{c.c.} \big] +$ $\mathbf{h}_{110} a^2 + \mathbf{h}_{001} \mu,$ $\mathbf{x}_0 = \mathbf{h}_{001} \mu$	

Table 4: